



# **NOVA II 1x1**

Single Pixel DMX Profiles

# **NOVA II 2x1**

Single Pixel and 2 Pixel (Light Engine) DMX Profiles

BLAIR-CG Color System

DMX Profile Specification V1.2

## Table of Contents

<b>DMX Profile Overview for Aputure OS II</b>	<b>6</b>
Control Channel Profiles	6
Detailed Breakdown of DMX Channels	6
No Effect Ranges	7
<b>Single Pixel Profiles - (NOVA II 1x1, NOVA II 2x1)</b>	<b>8</b>
Basic DMX Profiles - 1 Pixel	8
Profile 1: CCT & RGB - 8-bit (7 ch.)	8
Profile 2: CCT & RGB - 16-bit (14 ch.)	9
Profile 3: CCT & RGB & FX - 8-bit (13 ch.)	10
Profile 4: CCT & RGB & FX - 16-bit (20 ch.)	12
Profile 5: CCT & RGB & xy - 8-bit (10 ch.)	14
Profile 6: CCT & RGB & xy - 16-bit (20 ch.)	15
Profile 7: CCT & RGB & xy & FX - 8-bit (16 ch.)	16
Profile 8: CCT & RGB & xy & FX - 16-bit (26 ch.)	18
Profile 9: HSI - 8-bit (3 ch.)	20
Profile 10: HSI - 16-bit (6 ch.)	20
Profile 11: HSIC+ - 8-bit (5 ch.)	20
Profile 12: HSIC+ - 16-bit (10 ch.)	21
Profile 13: HSIC+ & FX - 8-bit (11 ch.)	22
Profile 14: HSIC+ & FX - 16-bit (16 ch.)	24
Profile 15: HSIC+ & xy - 8-bit (8 ch.)	26
Profile 16: HSIC+ & xy - 16-bit (16 ch.)	27
Profile 17: HSIC+ & xy & FX - 8-bit (14 ch.)	28
Profile 18: HSIC+ & xy & FX - 16-bit (22 ch.)	30
Profile 19: xy - 8-bit (3 ch.)	32
Profile 20: xy - 16-bit (6 ch.)	32
Profile 21: RGB - 8-bit (3 ch.)	32
Profile 22: RGB - 16-bit (6 ch.)	32
Profile 23: iRGB - 8-bit (4 ch.)	32
Profile 24: iRGB - 16-bit (8 ch.)	33
Profile 25: RGBAL - 8-bit (5 ch.)	33
Profile 26: RGBAL - 16-bit (10 ch.)	33
Profile 27: CCT+ 8-bit (3 ch.)	34
Profile 28: CCT+ 16-bit (6 ch.)	34
Profile 29: Source Mode - 8-bit (4 ch.)	35
Profile 30: Source Mode - 16-bit (7 ch.)	37
Profile 31: Legacy Gel - 8-bit (5 ch.)	39
Profile 32: Legacy Gel - 16-bit (6 ch.)	50
<b>Control Channel Profiles - 1 Pixel</b>	<b>61</b>
DMX Control Channel Chart	61
NOVA II 2x1, NOVA II 1x1	

Profile 41: CCT & RGB & Control - 8-bit (10 ch.)	64
Profile 42: CCT & RGB & Control - 16-bit (17 ch.)	66
Profile 43: CCT & RGB & FX & Control - 8-bit (16 ch.)	68
Profile 44: CCT & RGB & FX & Control - 16-bit (23 ch.)	70
Profile 45: CCT & RGB & xy & Control - 8-bit (13 ch.)	72
Profile 46: CCT & RGB & xy & Control - 16-bit (23 ch.)	74
Profile 47: CCT & RGB & xy & FX & Control - 8-bit (19 ch.)	76
Profile 48: CCT & RGB & xy & FX & Control - 16-bit (29 ch.)	79
Profile 49: HSI+ & Control - 8-bit (6 ch.)	82
Profile 50: HSI+ & Control - 16-bit (9 ch.)	83
Profile 51: HSIC+ & Control - 8-bit (8 ch.)	84
Profile 52: HSIC+ & Control - 16-bit (13 ch.)	86
Profile 53: HSIC+ & FX & Control - 8-bit (14 ch.)	88
Profile 54: HSIC+ & FX & Control - 16-bit (19 ch.)	90
Profile 55: HSIC+ & xy & Control - 8-bit (11 ch.)	92
Profile 56: HSIC+ & xy & Control - 16-bit (19 ch.)	94
Profile 57: HSIC+ & xy & FX & Control - 8-bit (17 ch.)	96
Profile 58: HSIC+ & xy & FX & Control - 16-bit (25 ch.)	98
Profile 59: xy & Control - 8-bit (6 ch.)	100
Profile 60: xy & Control - 16-bit (9 ch.)	101
Profile 61: RGB & Control - 8-bit (6 ch.)	102
Profile 62: RGB & Control - 16-bit (9 ch.)	103
Profile 63: iRGB & Control - 8-bit (7 ch.)	104
Profile 64: iRGB & Control - 16-bit (11 ch.)	105
Profile 65: RGBAL & Control - 8-bit (8 ch.)	106
Profile 66: RGBAL & Control - 16-bit (13 ch.)	107
Profile 67: CCT+ & Control - 8-bit (6 ch.)	108
Profile 68: CCT+ & Control - 16-bit (9 ch.)	109
Profile 69: Source Mode & Control - 8-bit (7 ch.)	111
Profile 70: Source Mode & Control - 16-bit (10 ch.)	114
Profile 71: Legacy Gel & Control - 8-bit (8 ch.)	117
Profile 72: Legacy Gel & Control - 16-bit (9 ch.)	128
<b>Color Space Profiles - 1 Pixel</b>	<b>140</b>
Profile 81: VRGB & Control - 8-bit (9 ch.)	140
Profile 82: VRGB & Control - 16-bit (14 ch.)	141
Profile 83: VRGB-I & Control - 8-bit (10 ch.)	143
Profile 84: VRGB & Control - 16-bit (16 ch.)	145
Profile 85: VRGB-CS & Control - 8-bit (7 ch.)	147
Profile 86: VRGB-CS & Control - 16-bit (10 ch.)	148
Profile 87: VRGB-709 & Control - 8-bit (6 ch.)	149
Profile 88: VRGB-709 - 16-bit (9 ch.)	150

Profile 89: VRGB-sRGB - 8-bit (6 ch.)	151
Profile 90: VRGB-sRGB - 16-bit (9 ch.)	152
<b>Color Space Chart</b>	<b>152</b>
<b>Light Engine Profile (NOVA II 2x1 only)</b>	<b>154</b>
Basic DMX Profiles - 2 Pixels	154
Profile 101: LE CCT & RGB - 8-bit - 2 Pixels (14 ch.)	154
Profile 102: LE CCT & RGB - 16-bit - 2 Pixels (28 ch.)	156
Profile 103: LE CCT & RGB & FX - 8-bit - 2 Pixels (20 ch.)	158
Profile 104: LE CCT & RGB & FX - 16-bit - 2 Pixels (34 ch.)	160
Profile 105: LE CCT & RGB & xy - 8-bit - 2 Pixels (20 ch.)	162
Profile 106: LE CCT & RGB & xy - 16-bit - 2 Pixels (40 ch.)	164
Profile 107: LE CCT & RGB & xy & FX - 8-bit - 2 Pixels (26 ch.)	166
Profile 108: LE CCT & RGB & xy & FX - 16-bit - 2 Pixels (46 ch.)	168
Profile 109: LE HSI - 8-bit - 2 Pixels (6 ch.)	171
Profile 110: LE HSI - 16-bit - 2 Pixels (12 ch.)	171
Profile 111: LE HSIC+ - 8-bit - 2 Pixels (10 ch.)	172
Profile 112: LE HSIC+ - 16-bit - 2 Pixels (20 ch.)	173
Profile 113: LE HSIC+ & FX - 8-bit - 2 Pixels (16 ch.)	174
Profile 114: LE HSIC+ & FX - 16-bit - 2 Pixels (26 ch.)	176
Profile 115: LE HSIC+ & xy - 8-bit - 2 Pixels (16 ch.)	178
Profile 116: LE HSIC+ & xy - 16-bit - 2 Pixels (32 ch.)	179
Profile 117: LE HSIC+ & xy & FX - 8-bit - 2 Pixels (22 ch.)	181
Profile 118: LE HSIC+ & xy & FX - 16-bit - 2 Pixels (38 ch.)	183
Profile 119: LE xy - 8-bit - 2 Pixels (6 ch.)	185
Profile 120: LE xy - 16-bit - 2 Pixels (12 ch.)	185
Profile 121: LE RGB - 8-bit - 2 Pixels (6 ch.)	185
Profile 122: LE RGB - 16-bit - 2 Pixels (12 ch.)	186
Profile 123: LE iRGB - 8-bit - 2 Pixels (8 ch.)	186
Profile 124: LE iRGB - 16-bit - 2 Pixels (16 ch.)	187
Profile 125: LE RGBAL - 8-bit - 2 Pixels (10 ch.)	187
Profile 126: LE RGBAL - 16-bit - 2 Pixels (20 ch.)	188
Profile 127: LE CCT+ - 8-bit - 2 Pixels (6 ch.)	189
Profile 128: LE CCT+ - 16-bit - 2 Pixels (12 ch.)	190
<b>Control Channel Profiles - 2 Pixels</b>	<b>191</b>
DMX Control Channel Chart	191
Profile 141: LE CCT & RGB & Control - 8-bit - 2 Pixels (17 ch.)	194
Profile 142: LE CCT & RGB & Control - 16-bit - 2 Pixels (31 ch.)	196
Profile 143: LE CCT & RGB & FX & Control - 8-bit - 2 Pixels (23 ch.)	198
Profile 144: LE CCT & RGB & FX & Control - 16-bit - 2 Pixels (37 ch.)	201
Profile 145: LE CCT & RGB & xy & Control - 8-bit - 2 Pixels (23 ch.)	204

NOVA II 2x1, NOVA II 1x1

Profile 146: LE CCT & RGB & xy & Control - 16-bit - 2 Pixels (43 ch.)	206
Profile 147: LE CCT & RGB & xy & FX & Control - 8-bit - 2 Pixels (29 ch.)	208
Profile 148: LE CCT & RGB & xy & FX & Control - 16-bit - 2 Pixels (49 ch.)	211
Profile 149: LE HSI+ & Control - 8-bit - 2 Pixels (9 ch.)	214
Profile 150: LE HSI - 16-bit - 2 Pixels (15 ch.)	215
Profile 151: LE HSIC+ & Control - 8-bit - 2 Pixels (13 ch.)	216
Profile 152: LE HSIC+ & Control - 16-bit - 2 Pixels (23 ch.)	218
Profile 153: LE HSIC+ & FX & Control - 8-bit - 2 Pixels (19 ch.)	220
Profile 154: LE HSIC+ & FX & Control - 16-bit - 2 Pixels (29 ch.)	223
Profile 155: LE HSIC+ & xy & Control - 8-bit - 2 Pixels (19 ch.)	226
Profile 156: LE HSIC+ & xy & Control - 16-bit - 2 Pixels (35 ch.)	228
Profile 157: LE HSIC+ & xy & FX & Control - 8-bit - 2 Pixels (25 ch.)	230
Profile 158: LE HSIC+ & xy & FX - 16-bit - 2 Pixels (41 ch.)	233
Profile 159: LE xy & Control - 8-bit - 2 Pixels (9 ch.)	236
Profile 160: LE xy & Control - 16-bit - 2 Pixels (15 ch.)	237
Profile 161: LE RGB & Control - 8-bit - 2 Pixels (9 ch.)	238
Profile 162: LE RGB & Control - 16-bit - 2 Pixels (15 ch.)	239
Profile 163: LE iRGB & Control - 8-bit - 2 Pixels (11 ch.)	240
Profile 164: LE iRGB & Control - 16-bit - 2 Pixels (19 ch.)	241
Profile 165: LE RGBAL & Control - 8-bit - 2 Pixels (13 ch.)	242
Profile 166: LE RGBAL & Control - 16-bit - 2 Pixels (23 ch.)	244
Profile 167: LE CCT+ & Control - 8-bit - 2 Pixels (9 ch.)	246
Profile 168: LE CCT+ & Control - 16-bit - 2 Pixels (15 ch.)	248
<b>Color Space Profiles - 2 Pixels</b>	<b>250</b>
Profile 181: VRGB & Control - 8-bit - 2 Pixels (12 ch.)	250
Profile 182: VRGB & Control - 16-bit - 2 Pixels (20 ch.)	252
Profile 183: VRGB-I & Control - 8-bit - 2 Pixels (13 ch.)	254
Profile 184: VRGB & Control - 16-bit - 2 Pixels (22 ch.)	256
Profile 185: VRGB-CS & Control - 8-bit - 2 Pixels (10 ch.)	257
Profile 186: VRGB-CS & Control - 16-bit - 2 Pixels (16 ch.)	259
Profile 187: VRGB-709 & Control - 8-bit - 2 Pixels (9 ch.)	261
Profile 188: VRGB-709 - 16-bit - 2 Pixels (15 ch.)	263
Profile 189: VRGB-sRGB - 8-bit - 2 Pixels (9 ch.)	264
Profile 190: VRGB-sRGB - 16-bit - 2 Pixels (15 ch.)	265
<b>Color Space Chart</b>	<b>266</b>
VRGB	267

# DMX Profile Overview for Aputure OS II

NOVA II product is a part of the OS II feature set with the same menu structure and experience, and DMX Profile Structure between Aputure products.

## For the NOVA II 1x1:

There are 3 sets of DMX Profiles:

### Single Pixel Profiles

1. Basic DMX Profiles - 1 Pixel
2. Control Channel DMX Profiles - 1 Pixel
3. Color Space DMX Profiles - 1 Pixel

## For the NOVA II 2x1:

There are 6 sets of DMX Profiles:

### Single Pixel Profiles

4. Basic DMX Profiles - 1 Pixel
5. Control Channel DMX Profiles - 1 Pixel
6. Color Space DMX Profiles - 1 Pixel

### Light Engine Profiles

7. Basic DMX Profiles - **LE Mode** - 2 Pixels
8. Control Channel DMX Profiles - **LE Mode** - 2 Pixels
9. Color Space DMX Profiles - **LE Mode** - 2 Pixels

## Control Channel Profiles

Profiles labeled “+Control” include three extra channels (Strobe, Control, and Fan). These profiles are ideal for users seeking advanced control methods.

OS II introduces DMX profiles with three additional control channels, depending on the product:

1. **Strobe Channel:** Enables strobing in any color.
2. **Control Channel:** Allows remote execution of light setting commands via a dedicated DMX channel.
3. **Fan Channel:** Adjusts the fan speed or behavior if the product is equipped with a fan.

## Detailed Breakdown of DMX Channels

### **Strobe Channel:**

The Strobe Channel enables strobe effects in any available color configuration, depending on the fixture's color mixing capabilities.

- **Example – Strobe a 20000K Color**

In Profile **CCT & RGB & Control - (10 ch.)**, set CCT (**Channel 2**) to 20,000K / 255. Set Strobe (**Channel 8**) to Rate of 25Hz / 255. The light will be at Max Strobe at 20,000K.

### **Control Channel:**

The Control Channel allows remote execution of fixture settings via predefined DMX values. To apply a command, assign the specified value to the Control Channel for 2.5 seconds, then reset it to 0. The fixture will issue a brief confirmation flash (red) upon successful execution.

NOVA II 2x1, NOVA II 1x1

- **Example – Turning DMX Smoothing Off:**  
In **CCT & RGB & Control - (10 ch.)**, set Control Channel (**Channel 9**) to **Value 27** for 2.5 seconds, then reset it to 0. The fixture will flash red at 20% brightness to indicate that DMX Smoothing has been disabled.
- **Example – Enabling DMX Smoothing:**  
To enable DMX Smoothing in **CCT & RGB & Control - (10 ch.)**, set **Channel 9** to **Value 30** for 2.5 seconds, then reset to 0. The red flash at 20% brightness confirms the change.

### Control Channel Signal Confirmation:

In cases where the confirmation flash is undesirable, such as when modifying multiple fixtures in enclosed spaces, the Signal Confirmation can be disabled by setting the Control Channel to **Value 15**, then back to 0. By default, the Signal Confirmation is enabled.

### Fan Channel:

The Fan Channel allows direct control over fan speed or behavior via DMX. Set a constant value to maintain a specific fan state, and modify the value as needed to adjust fan performance. In the System settings, the Fan mode must be set to “DMX Controlled”

- **Example – Setting the fan to Max**  
In **CCT & RGB & Control - (10 ch.)**, set the Fan Channel (**Channel 10**) to **Value 45**. The fan channel must be saved at the value. When changing the value in a cue, it can be used to cut the fan during takes.

## No Effect Ranges

In some DMX profiles, you may encounter a "No Effect" range at the beginning of a channel. This range is typically meant for slider boards, ensuring that when the slider is at 0, no effect is applied. These ranges should not be patched into lighting consoles, as they serve only to prevent unintended changes when the control is idle.

Channel	Function	Value	Percent	Description
X	±Green	0 - 255	0 - 100	-G to 0G to +G
		0 - 10	0 - 4	No Effect*
		11-20	5 - 8	Full Minus Green
		21 - 119	9 - 47	-99% - -1%
		120 - 145	48 - 57	0% Neutral
		146 - 244	58 - 96	1% - 99%
		245 - 255	97 - 100	Full Plus Green

# Single Pixel Profiles - (NOVA II 1x1, NOVA II 2x1)

## Basic DMX Profiles - 1 Pixel

### Profile 1: CCT & RGB - 8-bit (7 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
5	Red	0 - 255	0 - 100	Red Intensity	100% / 255
6	Green	0 - 255	0 - 100	Green Intensity	100% / 255
7	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
				*Do not patch "No Effect" range into consoles	

## Profile 2: CCT & RGB - 16-bit (14 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
9 / 10	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
11 / 12	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
13 / 14	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
				*Do not patch "No Effect" range into consoles	

### Profile 3: CCT & RGB & FX - 8-bit (17 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
5	Red	0 - 255	0 - 100	Red Intensity	100% / 255
6	Green	0 - 255	0 - 100	Green Intensity	100% / 255
7	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>FX</b>					
8	Crossfade 2	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
9	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Explosion	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Other Effects	0 - 69	0 - 27	Loop	
		70 - 255	28 - 100	Stop	
10	Effect Selection	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	

		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
		150 - 255	61 - 100	Reserved	
<b>11</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>12</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>13</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0
<b>14</b>	<b>Effect Parameter 4</b>	0 - 255	0 - 100		0% / 0
<b>15</b>	<b>Effect Parameter 5</b>	0 - 255	0 - 100		0% / 0
<b>16</b>	<b>Effect Parameter 6</b>	0 - 255	0 - 100		0% / 0
<b>17</b>	<b>Effect Parameter 7</b>	0 - 255	0 - 100		0% / 0
					*Do not patch "No Effect" range into consoles

## Profile 4: CCT & RGB & FX - 16-bit (29 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
9 / 10	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
11 / 12	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
13 / 14	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>FX</b>					
15	Crossfade 2	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
16	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Explosion	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Other Effects	0 - 69	0 - 27	Loop	
		70 - 255	28 - 100	Stop	
17	Effect Selection	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	

NOVA II 2x1, NOVA II 1x1

		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
		150 - 255	61 - 100	Reserved	
18	Effect Parameter 1	0 - 255	0 - 100	See Effect Chart	0% / 0
19	Effect Parameter 2	0 - 255	0 - 100		0% / 0
20	Effect Parameter 3	0 - 255	0 - 100		0% / 0
21	Effect Parameter 4	0 - 255	0 - 100		0% / 0
22	Effect Parameter 5	0 - 255	0 - 100		0% / 0
23	Effect Parameter 6	0 - 255	0 - 100		0% / 0
24	Effect Parameter 7	0 - 255	0 - 100		0% / 0
25	Effect Parameter 8	0 - 255	0 - 100		0% / 0
26	Effect Parameter 9	0 - 255	0 - 100		0% / 0
27	Effect Parameter 10	0 - 255	0 - 100		0% / 0
28	Effect Parameter 11	0 - 255	0 - 100		0% / 0
29	Effect Parameter 12	0 - 255	0 - 100		0% / 0
				*Do not patch "No Effect" range into consoles	

## Profile 5: CCT & RGB & xy - 8-bit (10 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
5	Red	0 - 255	0 - 100	Red Intensity	100% / 255
6	Green	0 - 255	0 - 100	Green Intensity	100% / 255
7	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
8	Crossfade 2	0 - 255	0 - 100	CCTRGB to xy	0% / 0
9	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
10	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
				*Do not patch "No Effect" range into consoles	

## Profile 6: CCT & RGB & xy - 16-bit (20 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
9 / 10	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
11 / 12	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
13 / 14	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
15 / 16	Crossfade 2	0 - 65535	0 - 100	CCTRGB to xy	0
17 / 18	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
19 / 20	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
				*Do not patch "No Effect" range into consoles	

## Profile 7: CCT & RGB & xy & FX - 8-bit (20 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
5	Red	0 - 255	0 - 100	Red Intensity	100% / 255
6	Green	0 - 255	0 - 100	Green Intensity	100% / 255
7	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
8	Crossfade 2	0 - 255	0 - 100	CCTRGB to xy	0% / 0
9	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
10	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>FX</b>					
11	Crossfade 3	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
12	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Explosion	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Other Effects	0 - 69	0 - 27	Loop	
70 - 255		28 - 100	Stop		
13	Effect Selection	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	

NOVA II 2x1, NOVA II 1x1

		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
		150 - 255	61 - 100	Reserved	
<b>14</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>15</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>16</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0
<b>17</b>	<b>Effect Parameter 4</b>	0 - 255	0 - 100		0% / 0
<b>18</b>	<b>Effect Parameter 5</b>	0 - 255	0 - 100		0% / 0
<b>19</b>	<b>Effect Parameter 6</b>	0 - 255	0 - 100		0% / 0
<b>20</b>	<b>Effect Parameter 7</b>	0 - 255	0 - 100		0% / 0
				*Do not patch "No Effect" range into consoles	

## Profile 8: CCT & RGB & xy & FX - 16-bit (35 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
9 / 10	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
11 / 12	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
13 / 14	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
15 / 16	Crossfade 2	0 - 65535	0 - 100	CCTRGB to xy	0
17 / 18	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
19 / 20	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>FX</b>					
21	Crossfade 3	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
22	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Explosion	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Other Effects	0 - 69	0 - 27	Loop	
70 - 255		28 - 100	Stop		
23	Effect Selection	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	

NOVA II 2x1, NOVA II 1x1

		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
		150 - 255	61 - 100	Reserved	
<b>24</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>25</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>26</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0
<b>27</b>	<b>Effect Parameter 4</b>	0 - 255	0 - 100		0% / 0
<b>28</b>	<b>Effect Parameter 5</b>	0 - 255	0 - 100		0% / 0
<b>29</b>	<b>Effect Parameter 6</b>	0 - 255	0 - 100		0% / 0
<b>30</b>	<b>Effect Parameter 7</b>	0 - 255	0 - 100		0% / 0
<b>31</b>	<b>Effect Parameter 8</b>	0 - 255	0 - 100		0% / 0
<b>32</b>	<b>Effect Parameter 9</b>	0 - 255	0 - 100		0% / 0
<b>33</b>	<b>Effect Parameter 10</b>	0 - 255	0 - 100		0% / 0
<b>34</b>	<b>Effect Parameter 11</b>	0 - 255	0 - 100		0% / 0
<b>35</b>	<b>Effect Parameter 12</b>	0 - 255	0 - 100		0% / 0
				*Do not patch "No Effect" range into consoles	

### Profile 9: HSI - 8-bit (3 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>CCT is Locked at 6500K</b>					
1	Intensity	0 - 255	0 - 100	0 - 100	0% / 0
2	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
3	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0

### Profile 10: HSI - 16-bit (6 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>CCT is Locked at 6500K</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100	0% / 0
3 / 4	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
5 / 6	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0

### Profile 11: HSIC+ - 8-bit (5 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
5	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
				*Do not patch "No Effect" range into consoles	

## Profile 12: HSIC+ - 16-bit (10 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
9 / 10	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
				*Do not patch "No Effect" range into consoles	

## Profile 13: HSIC+ & FX - 8-bit (15 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
5	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
<b>FX</b>					
6	Crossfade	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
7	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Explosion	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Other Effects	0 - 69	0 - 27	Loop	
70 - 255		28 - 100	Stop		
8	Effect Selection	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	

NOVA II 2x1, NOVA II 1x1

		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
		150 - 255	61 - 100	Reserved	
<b>9</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>10</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>11</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0
<b>12</b>	<b>Effect Parameter 4</b>	0 - 255	0 - 100		0% / 0
<b>13</b>	<b>Effect Parameter 5</b>	0 - 255	0 - 100		0% / 0
<b>14</b>	<b>Effect Parameter 6</b>	0 - 255	0 - 100		0% / 0
<b>15</b>	<b>Effect Parameter 7</b>	0 - 255	0 - 100		0% / 0
				*Do not patch "No Effect" range into consoles	

## Profile 14: HSIC+ & FX - 16-bit (25 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
9 / 10	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
<b>FX</b>					
11	Crossfade	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
12	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Explosion	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Other Effects	0 - 69	0 - 27	Loop	
70 - 255		28 - 100	Stop		
13	Effect Selection	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	

		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
		150 - 255	61 - 100	Reserved	
<b>14</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>15</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>16</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0
<b>17</b>	<b>Effect Parameter 4</b>	0 - 255	0 - 100		0% / 0
<b>18</b>	<b>Effect Parameter 5</b>	0 - 255	0 - 100		0% / 0
<b>19</b>	<b>Effect Parameter 6</b>	0 - 255	0 - 100		0% / 0
<b>20</b>	<b>Effect Parameter 7</b>	0 - 255	0 - 100		0% / 0
<b>21</b>	<b>Effect Parameter 8</b>	0 - 255	0 - 100		0% / 0
<b>22</b>	<b>Effect Parameter 9</b>	0 - 255	0 - 100		0% / 0
<b>23</b>	<b>Effect Parameter 10</b>	0 - 255	0 - 100		0% / 0
<b>24</b>	<b>Effect Parameter 11</b>	0 - 255	0 - 100		0% / 0
<b>25</b>	<b>Effect Parameter 12</b>	0 - 255	0 - 100		0% / 0
				*Do not patch "No Effect" range into consoles	

## Profile 15: HSIC+ & xy - 8-bit (8 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
5	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
6	Crossfade	0 - 255	0 - 100	HSIC+ to xy	0% / 0
7	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
8	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
				*Do not patch "No Effect" range into consoles	

## Profile 16: HSIC+ & xy - 16-bit (16 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
9 / 10	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
11 / 12	Crossfade	0 - 65535	0 - 100	HSIC+ to xy	0% / 0
13 / 14	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
15 / 16	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
				*Do not patch "No Effect" range into consoles	

## Profile 17: HSIC+ & xy & FX - 8-bit (18 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
5	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
6	Crossfade	0 - 255	0 - 100	HSIC+ to xy	0% / 0
7	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
8	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>FX</b>					
9	Crossfade 2	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
10	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Explosion	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Other Effects	0 - 69	0 - 27	Loop	
		70 - 255	28 - 100	Stop	
11	Effect Selection	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	

NOVA II 2x1, NOVA II 1x1

		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
		150 - 255	61 - 100	Reserved	
<b>12</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>13</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>14</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0
<b>15</b>	<b>Effect Parameter 4</b>	0 - 255	0 - 100		0% / 0
<b>16</b>	<b>Effect Parameter 5</b>	0 - 255	0 - 100		0% / 0
<b>17</b>	<b>Effect Parameter 6</b>	0 - 255	0 - 100		0% / 0
<b>18</b>	<b>Effect Parameter 7</b>	0 - 255	0 - 100		0% / 0
					*Do not patch "No Effect" range into consoles

## Profile 18: HSIC+ & xy & FX - 16-bit (31 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
9 / 10	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
11 / 12	Crossfade	0 - 65535	0 - 100	HSIC+ to xy	0% / 0
13 / 14	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
15 / 16	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>FX</b>					
17	Crossfade 2	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
18	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Explosion	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Other Effects	0 - 69	0 - 27	Loop	
		70 - 255	28 - 100	Stop	
19	Effect Selection	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	

		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
		150 - 255	61 - 100	Reserved	
<b>20</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>21</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>22</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0
<b>23</b>	<b>Effect Parameter 4</b>	0 - 255	0 - 100		0% / 0
<b>24</b>	<b>Effect Parameter 5</b>	0 - 255	0 - 100		0% / 0
<b>25</b>	<b>Effect Parameter 6</b>	0 - 255	0 - 100		0% / 0
<b>26</b>	<b>Effect Parameter 7</b>	0 - 255	0 - 100		0% / 0
<b>27</b>	<b>Effect Parameter 8</b>	0 - 255	0 - 100		0% / 0
<b>28</b>	<b>Effect Parameter 9</b>	0 - 255	0 - 100		0% / 0
<b>29</b>	<b>Effect Parameter 10</b>	0 - 255	0 - 100		0% / 0
<b>30</b>	<b>Effect Parameter 11</b>	0 - 255	0 - 100		0% / 0
<b>31</b>	<b>Effect Parameter 12</b>	0 - 255	0 - 100		0% / 0
				*Do not patch "No Effect" range into consoles	

### Profile 19: xy - 8-bit (3 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
3	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)

### Profile 20: xy - 16-bit (6 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
5 / 6	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)

### Profile 21: RGB - 8-bit (3 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>CCT is Locked at 6500K</b>					
1	Red	0 - 255	0 - 100	Red Intensity	100% / 255
2	Green	0 - 255	0 - 100	Green Intensity	100% / 255
3	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255

### Profile 22: RGB - 16-bit (6 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>CCT is Locked at 6500K</b>					
1 / 2	Red	0 - 65535	0 - 100	0 - 100%	100% / 65535
3 / 4	Green	0 - 65535	0 - 100	0 - 100%	100% / 65535
5 / 6	Blue	0 - 65535	0 - 100	0 - 100%	100% / 65535

### Profile 23: iRGB - 8-bit (4 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>CCT is Locked at 6500K</b>					
1	Intensity	0 - 255	0 - 100	Global Intensity	0% / 0
2	Red	0 - 255	0 - 100	Red Intensity	100% / 255
3	Green	0 - 255	0 - 100	Green Intensity	100% / 255
4	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255

NOVA II 2x1, NOVA II 1x1

### **Profile 24: iRGB - 16-bit (8 ch.)**

Channel	Function	Value	Percent	Description	Default % / DMX
<b>CCT is Locked at 6500K</b>					
1 / 2	Intensity	0 - 65535	0 - 100	Global Intensity	0% / 0
3 / 4	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
5 / 6	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
7 / 8	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535

### **Profile 25: RGBAL - 8-bit (5 ch.)**

Channel	Function	Value	Percent	Description	Default % / DMX
1	Red	0 - 255	0 - 100	Red Intensity	100% / 255
2	Green	0 - 255	0 - 100	Green Intensity	100% / 255
3	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
4	Amber	0 - 255	0 - 100	Amber Intensity	100% / 255
5	Lime	0 - 255	0 - 100	Lime Intensity	100% / 255

### **Profile 26: RGBAL - 16-bit (10 ch.)**

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
3 / 4	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
5 / 6	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
7 / 8	Amber	0 - 65535	0 - 100	Amber Intensity	100% / 65535
9 / 10	Lime	0 - 65535	0 - 100	Lime Intensity	100% / 65535

### Profile 27: CCT+ 8-bit (3 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
				*Do not patch "No Effect" range into consoles	

### Profile 28: CCT+ 16-bit (6 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
				*Do not patch "No Effect" range into consoles	

## Profile 29: Source Mode - 8-bit (4 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	Source	0 - 2	0 - 1	Tungsten Bulb	0% / 0
		3 - 5	2 - 3	Incandescent	
		6 - 8	4 - 5	Halogen	
		9 - 11	6 - 7	Antique Bulb	
		12 - 14	8 - 9	Warm Antique Bulb	
		15 - 17	10 - 11	Christmas Lights	
		18 - 20	12 - 13	Night Light	
		21 - 23	14 - 15	Infrared Heat Lamp	
		24 - 26	16 - 17	Grow Light	
		27 - 29	18 - 19	CFL Soft White	
		30 - 32	20 - 21	CFL Bright White	
		33 - 35	22 - 23	CFL Cool White	
		36 - 38	24 - 25	CFL Daylight	
		39 - 41	26 - 27	Cool White 1	
		42 - 44	28 - 29	Cool White 2	
		45 - 47	30 - 31	Cool White 3	
		48 - 50	32 - 33	Warm White	
		51 - 53	34 - 35	CFL Blacklight	
		54 - 56	36 - 37	HMI	
		57 - 59	38 - 39	High Pressure Sodium	
		60 - 62	40 - 41	Low Pressure Sodium	
63 - 65	42 - 43	Mercury Vapor			
66 - 68	44 - 45	Metal Halide			
69 - 71	46 - 47	Ceramic			
72 - 74	48 - 49	Carbon Arc			
75 - 77	50 - 51	Xenon			
78 - 80	52 - 53	Candle			
81 - 83	54 - 55	Gas Fire			
84 - 86	56 - 57	Sun Direct			
87 - 89	58 - 59	Sun Overcast			
90 - 92	60 - 61	Sun Blue Hour			

NOVA II 2x1, NOVA II 1x1

		93 - 95	62 - 63	Mobile Phone	
		96 - 98	64 - 65	Computer Monitor	
		99 - 101	66 - 67	Electroluminescence	
		102 - 104	68 - 69	Blow Torch	
		105 - 107	70 - 71	Road Flare	
		108 - 110	72 - 73	Amber Caution	
		111-113	74 - 75	Green Traffic Light	
		114 - 116	76 - 77	Yellow Traffic Light	
		117 - 119	78 - 79	Red Traffic Light	
		120 - 122	80 - 81	Blue Glow Stick	
		123 - 125	82 - 83	Green Glow Stick	
		126 - 128	84 - 85	Red Glow Stick	
		129 - 131	86 - 87	Yellow Glow Stick	
		132 - 134	88 - 89	Pink Glow Stick	
		135 - 137	90 - 91	Violet Glow Stick	
		138 - 255	92 - 100	RESERVED	
<b>3</b>	<b>x Coordinate</b>	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
<b>4</b>	<b>y Coordinate</b>	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)

## Profile 30: Source Mode - 16-bit (7 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3	Source	0 - 2	0 - 1	Tungsten Bulb	0% / 0
		3 - 5	2 - 3	Incandescent	
		6 - 8	4 - 5	Halogen	
		9 - 11	6 - 7	Antique Bulb	
		12 - 14	8 - 9	Warm Antique Bulb	
		15 - 17	10 - 11	Christmas Lights	
		18 - 20	12 - 13	Night Light	
		21 - 23	14 - 15	Infrared Heat Lamp	
		24 - 26	16 - 17	Grow Light	
		27 - 29	18 - 19	CFL Soft White	
		30 - 32	20 - 21	CFL Bright White	
		33 - 35	22 - 23	CFL Cool White	
		36 - 38	24 - 25	CFL Daylight	
		39 - 41	26 - 27	Cool White 1	
		42 - 44	28 - 29	Cool White 2	
		45 - 47	30 - 31	Cool White 3	
		48 - 50	32 - 33	Warm White	
		51 - 53	34 - 35	CFL Blacklight	
		54 - 56	36 - 37	HMI	
		57 - 59	38 - 39	High Pressure Sodium	
60 - 62	40 - 41	Low Pressure Sodium			
63 - 65	42 - 43	Mercury Vapor			
66 - 68	44 - 45	Metal Halide			
69 - 71	46 - 47	Ceramic			
72 - 74	48 - 49	Carbon Arc			
75 - 77	50 - 51	Xenon			
78 - 80	52 - 53	Candle			
81 - 83	54 - 55	Gas Fire			
84 - 86	56 - 57	Sun Direct			
87 - 89	58 - 59	Sun Overcast			
90 - 92	60 - 61	Sun Blue Hour			

NOVA II 2x1, NOVA II 1x1

		93 - 95	62 - 63	Mobile Phone	
		96 - 98	64 - 65	Computer Monitor	
		99 - 101	66 - 67	Electroluminescence	
		102 - 104	68 - 69	Blow Torch	
		105 - 107	70 - 71	Road Flare	
		108 - 110	72 - 73	Amber Caution	
		111-113	74 - 75	Green Traffic Light	
		114 - 116	76 - 77	Yellow Traffic Light	
		117 - 119	78 - 79	Red Traffic Light	
		120 - 122	80 - 81	Blue Glow Stick	
		123 - 125	82 - 83	Green Glow Stick	
		126 - 128	84 - 85	Red Glow Stick	
		129 - 131	86 - 87	Yellow Glow Stick	
		132 - 135	88 - 89	Pink Glow Stick	
		136 - 138	90 - 91	Violet Glow Stick	
		139 - 255	92 - 100	RESERVED	
<b>4 / 5</b>	<b>x Coordinate</b>	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
<b>6 / 7</b>	<b>y Coordinate</b>	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)

## Profile 31: Legacy Gel - 8-bit (5 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 126	0 - 50	3200K	0% / 3200K
		127 - 255	51 - 100	5600K	
3	Rosco / Lee	0 - 29	0 - 12	Rosco	0% / 0
		30 - 59	13 - 24	Lee	
		60 - 255	25 - 100	Reserved	
4	Series	0 - 9	0 - 4	R-Col.corr / L-Col.Corr	0% / 0
		10 - 19	5 - 8	R-Cal Color / L-Cal. Filter	
		20 - 29	9 - 12	R-Storaro / L-600 Series	
		30 - 39	13 - 16	R-Cinelux / L-Cosmetic	
		40 - 49	17 - 20	R-reserved / L-700 Series	
		50 - 255	21 - 100	Reserved	
5	Category	0 - 255	0 - 100	See GEL Category Tables Below	0% / 0
<b>GEL Category 1 : Rosco - Color Correction</b>					
5		0-1		Full CTB	0% / 0
		2-3		3/4 CTB	
		4-5		1/2 CTB	
		6-7		1/3 CTB	
		8-9		1/4 CTB	
		10-11		1/8 CTB	
		12-13		Double CTB	
		14-15		Full CTO	
		16-17		3/4 CTO	
		18-19		1/2 CTO	
		20-21		1/4 CTO	
		22-23		1/8 CTO	
		24-25		Double CTO	
		26-27		Full CTS	
		28-29		1/2 CTS	

NOVA II 2x1, NOVA II 1x1

		30-31		1/4 CTS	
		32-33		1/8 CTS	
		34-35		Full Plusgreen	
		36-37		1/2 Plusgreen	
		38-39		1/4 Plusgreen	
		40-41		1/8 Plusgreen	
		42-43		Full Minusgreen	
		44-45		3/4 Minusgreen	
		46-47		1/2 Minusgreen	
		48-49		1/4 Minusgreen	
		50-51		1/8 Minusgreen	
		52-53		Fluorofilter	
		54-55		Industrial Vapor	
		56-57		Urban Vapor	
		58-59		Tough Y1	
		60-61		Tough MT 54	
		62-63		Tough MTY	
		64-65		Tough MT2	
		66-255		Reserved	
<b>GEL Category 1 : Rosco - Cal Color</b>					
<b>5</b>		0-1		15 Blue	
		2-3		30 Blue	
		4-5		60 Blue	
		6-7		90 Blue	
		8-9		7 Cyan	
		10-11		15 Cyan	
		12-13		30 Cyan	
		14-15		60 Cyan	
		16-17		90 Cyan	
		18-19		15 Green	
		20-21		30 Green	
		22-23		60 Green	
		24-25		90 Green	
		26-27		15 Yellow	

NOVA II 2x1, NOVA II 1x1

		28-29		30 Yellow	
		30-31		60 Yellow	
		32-33		90 Yellow	
		34-35		15 Red	
		36-37		30 Red	
		38-39		60 Red	
		40-41		90 Red	
		42-43		15 Magenta	
		44-45		30 Magenta	
		46-47		60 Magenta	
		48-49		90 Magenta	
		50-51		15 Pink	
		52-53		30 Pink	
		54-55		60 Pink	
		56-57		90 Pink	
		58-59		15 Lavender	
		60-61		30 Lavender	
		62-63		60 Lavender	
		64-65		90 Lavender	
		66-255		Reserved	
<b>GEL Category 3 : Rosco - Storaro</b>					
<b>5</b>		0-1		VS Red	
		2-3		VS Orange	
		4-5		VS Yellow	
		6-7		VS Green	
		8-9		VS Cyan	
		10-11		VS Azure	
		12-13		VS Blue	
		14-15		VS Indigo	
		16-17		VS Violet	
		18-19		VS Magenta	
		20-255		Reserved	
	<b>GEL Category 4 : Rosco - Cinelux</b>				
<b>5</b>		0-1		Bastard Amber	

NOVA II 2x1, NOVA II 1x1

		2-3		Pale Bastard Amber	
		4-5		No Color Straw	
		6-7		Pale Gold	
		8-9		Daffodil	
		10-11		Straw	
		12-13		Light Amber	
		14-15		Gallo Gold	
		16-17		Light Flame	
		18-19		Flame	
		20-21		Mayan Sun	
		22-23		Golden Amber	
		24-25		Soft Golden Amber	
		26-27		Orange	
		28-29		Henna Sky	
		30-31		Light Red	
		32-33		No Color Pink	
		34-35		Blush Pink	
		36-37		Flesh Pink	
		38-39		Pale Rose Pink	
		40-41		Salmon	
		42-43		Deep Salmon	
		44-45		Middle Rose	
		46-47		Light Rose Purple	
		48-49		Surprise Pink	
		50-51		No Color Blue	
		52-53		Clearwater	
		54-55		Booster Blue	
		56-57		Tipton Blue	
		58-59		Blue Bell	
		60-61		Daylight Blue	
		62-63		Tharon Delft Blue	
		64-65		Cerulean Blue	
		66-67		Bermuda Blue	
		68-69		Green Blue	

NOVA II 2x1, NOVA II 1x1

		70-71		Alice Blue	
		72-73		Primary Blue	
		74-75		Baldassari Blue	
		76-77		Medium Blue	
		78-79		Pale Yellow Green	
		80-81		Light Green	
		82-83		Moss Green	
		84-85		Primary Green	
		86-87		Turquoise	
		88-89		Blue Green	
		90-91		Chocolate	
		92-255		Reserved	

**GEL Category 1 : LEE - Color Correction**

<b>5</b>		0-1		Double CTB	
		2-3		Full CTB	
		4-5		3/4 CTB	
		6-7		1/2 CTB	
		8-9		1/4 CTB	
		10-11		1/8 CTB	
		12-13		Double CTO	
		14-15		Full CTO	
		16-17		3/4 CTO	
		18-19		1/2 CTO	
		20-21		1/4 CTO	
		22-23		1/8 CTO	
		24-25		1 1/2 CTB	
		26-27		1 1/2 CTO	
		28-29		Full CTS	
		30-31		1/2 CTS	
		32-33		1/4 CTS	
		34-35		1/8 CTS	
		36-37		Full CTO + .3 ND	
		38-39		Full CTO + .6 ND	
	40-41		L.C.T. Yellow (Y1)		

NOVA II 2x1, NOVA II 1x1

		42-43		White Flame Green	
		44-45		LEE Fluorescent Green	
		46-47		Super Correction L.C.T. Yellow	
		48-49		Super Correction W.F. Green	
		50-51		H.M.I. (to Tungsten)	
		52-53		C.I.D. (to Tungsten)	
		54-55		C.S.I. (to Tungsten)	
		56-57		LEE Fluorescent 5700 Kelvin	
		58-59		LEE Fluorescent 4300 Kelvin	
		60-61		LEE Fluorescent 3600 Kelvin	
		62-63		LEE Plus Green	
		64-65		1/2 Plus Green	
		66-67		1/4 Plus Green	
		68-69		1/8 Plus Green	
		70-71		LEE Minus Green	
		72-73		1/2 Minus Green	
		74-75		1/4 Minus Green	
		76-77		1/8 Minus Green	
		78-255		Reserved	
<b>GEL Category 2 : LEE - Color Filters</b>					
<b>5</b>		0-1		Rose Pink	
		2-3		Lavender Tint	
		4-5		Medium Bastard Amber	
		6-7		Pale Yellow	
		8-9		Dark Salmon	
		10-11		Pale Amber Gold	
		12-13		Medium Yellow	
		14-15		Straw Tint	
		16-17		Surprise Peach	
		18-19		Fire	

	20-21	Medium Amber
	22-23	Gold Amber
	24-25	Dark Amber
	26-27	Scarlet
	28-29	Sunset Red
	30-31	Bright Red
	32-33	Light Pink
	34-35	Medium Pink
	36-37	Dark Magenta
	38-39	Rose Purple
	40-41	Light Lavender
	42-43	Paler Lavender
	44-45	Lavender
	46-47	Mist Blue
	48-49	Pale Blue
	50-51	Sky Blue
	52-53	Evening Blue
	54-55	Just Blue
	56-57	Deeper Blue
	58-59	Lime Green
	60-61	Moss Green
	62-63	Dark Yellow Green
	64-65	Spring Yellow
	66-67	Yellow
	68-69	Light Amber
	70-71	Straw
	72-73	Deep Amber
	74-75	Primary Red
	76-77	Light Rose
	78-79	English Rose
	80-81	Light Salmon
	82-83	Middle Rose
	84-85	Dark Pink
	86-87	Magenta

NOVA II 2x1, NOVA II 1x1

	88-89	Peacock Blue
	90-91	Steel Blue
	92-93	Light Blue
	94-95	Deep Blue
	96-97	LEE Green
	98-99	Fern Green
	100-101	Dark Green
	102-103	Smokey Pink
	104-105	Bright Pink
	106-107	Marine Blue
	108-109	Golden Amber
	110-111	Deep Golden Amber
	112-113	Pale Lavender
	114-115	Special Lavender
	116-117	Pale Green
	118-119	Summer Blue
	120-121	Pale Violet
	122-123	Pale Navy Blue
	124-125	No Color Blue
	126-127	Apricot
	128-129	Bright Rose
	130-131	Gold Tint
	132-133	Pale Gold
	134-135	Pale Salmon
	136-137	Pale Rose
	138-139	Chocolate
	140-141	Pink
	142-143	No Color Straw
	144-145	Slate Blue
	146-147	Bastard Amber
	148-149	Flame Red
	150-151	Daylight Blue
	152-153	Lilac Tint
	154-155	Deep Lavender

NOVA II 2x1, NOVA II 1x1

		156-157		Dark Steel Blue	
		158-159		Loving Amber	
		160-161		Dark Lavender	
		162-163		Light Red	
		164-165		Flesh Pink	
		166-167		Surprise Pink	
		168-169		Zenith Blue	
		170-171		True Blue	
		172-173		Alice Blue	
		174-175		Palace Blue	
		176-177		Regal Blue	
		178-255		Reserved	
<b>GEL Category 3 : LEE - 600 Series</b>					
<b>5</b>		0-1		Arctic White	
		2-3		Silver	
		4-5		Platinum	
		6-7		Moonlight White	
		8-9		Full CT 85	
		10-11		Industry Sodium	
		12-13		HI Sodium	
		14-15		Urban Sodium	
		16-17		LO Sodium	
		18-255		Reserved	
<b>GEL Category 4 : LEE - Cosmetic Filters</b>					
<b>5</b>		0-1		Cosmetic Peach	
		2-3		Cosmetic Silver Rose	
		4-5		Cosmetic Rouge	
		6-7		Cosmetic Highlight	
		8-9		Cosmetic Silver Moss	
		10-11		Cosmetic Aqua Blue	
		12-13		Lily Frost	
		14-15		Shanklin Frost	
		16-17		Half Shanklin Frost	
		18-19		Durham Daylight Frost	

NOVA II 2x1, NOVA II 1x1

		20-21		Hampshire Rose	
		22-23		Durham Frost	
		24-25		Soft Amber Key 1	
		26-27		Soft Amber Key 2	
		28-29		Moroccan Frost	
		30-31		Blue Diffusion	
		32-33		Blue Frost	
		34-35		Daylight Blue Frost	
		36-255		Reserved	
<b>GEL Category 5 : LEE - 700 Series</b>					
<b>5</b>		0-1		Perfect Lavender	
		2-3		Provence	
		4-5		Special Pale Lavender	
		6-7		Cold Lavender	
		8-9		Lily	
		10-11		King Fals Lavender	
		12-13		Cool Lavender	
		14-15		Electric Lilac	
		16-17		Spir Special Blue	
		18-19		Cold Blue	
		20-21		Bedford Blue	
		22-23		Elysian Blue	
		24-25		Cabana Blue	
		26-27		Mikkel Blue	
		28-29		Colour Wash Blue	
		30-31		Berry Blue	
		32-33		Virgin Blue	
		34-35		Ocean Blue	
		36-37		Old Steel Blue	
		38-39		Steel Green	
	40-41		Liberty Green		
	42-43		Dirty Ice		
	44-45		Damp Squib		
	46-47		JAS Green		

NOVA II 2x1, NOVA II 1x1

		48-49		Bram Brown	
		50-51		Dirty White	
		52-53		Brown	
		54-55		Easy White	
		56-57		Seedy Pink	
		58-59		Wheat	
		60-61		Sun Colour Straw	
		62-63		LEE Yellow	
		64-65		Cardbox Amber	
		66-67		Nectarine	
		68-69		Millenium Gold	
		70-71		Bastard Pink	
		72-73		Terry Red	
		74-75		Blood Red	
		76-77		Moroccan Pink	
		78-79		Pretty n'Pink	
		80-81		Magical Magenta	
		82-255		Reserved	

## Profile 32: Legacy Gel - 16-bit (6 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3	CCT	0 - 126	0 - 50	3200K	3200K / 0
		127 - 255	51 - 100	5600K	
4	Rosco / Lee	0 - 29	0 - 12	Rosco	
		30 - 59	13 - 24	Lee	
		60 - 255	25 - 100	Reserved	
5	Series	0 - 9	0 - 4	R-Col.corr / L-Col.Corr	
		10 - 19	5 - 8	R-Cal Color / L-Cal. Filter	
		20 - 29	9 - 12	R-Storaro / L-600 Series	
		30 - 39	13 - 16	R-Cinelux / L-Cosmetic	
		40 - 49	17 - 20	R-reserved / L-700 Series	
		50 - 255	21 - 100	Reserved	
6	Category	0 - 255	0 - 100	See GEL Category Tables Below	
<b>GEL Category 1 : Rosco - Color Correction</b>					
6		0-1		Full CTB	
		2-3		3/4 CTB	
		4-5		1/2 CTB	
		6-7		1/3 CTB	
		8-9		1/4 CTB	
		10-11		1/8 CTB	
		12-13		Double CTB	
		14-15		Full CTO	
		16-17		3/4 CTO	
		18-19		1/2 CTO	
		20-21		1/4 CTO	
		22-23		1/8 CTO	
		24-25		Double CTO	
		26-27		Full CTS	
	28-29		1/2 CTS		

NOVA II 2x1, NOVA II 1x1

		30-31		1/4 CTS	
		32-33		1/8 CTS	
		34-35		Full Plusgreen	
		36-37		1/2 Plusgreen	
		38-39		1/4 Plusgreen	
		40-41		1/8 Plusgreen	
		42-43		Full Minusgreen	
		44-45		3/4 Minusgreen	
		46-47		1/2 Minusgreen	
		48-49		1/4 Minusgreen	
		50-51		1/8 Minusgreen	
		52-53		Fluorofilter	
		54-55		Industrial Vapor	
		56-57		Urban Vapor	
		58-59		Tough Y1	
		60-61		Tough MT 54	
		62-63		Tough MTY	
		64-65		Tough MT2	
		66-255		Reserved	
<b>GEL Category 1 : Rosco - Cal Color</b>					
<b>6</b>		0-1		15 Blue	
		2-3		30 Blue	
		4-5		60 Blue	
		6-7		90 Blue	
		8-9		7 Cyan	
		10-11		15 Cyan	
		12-13		30 Cyan	
		14-15		60 Cyan	
		16-17		90 Cyan	
		18-19		15 Green	
		20-21		30 Green	
		22-23		60 Green	
		24-25		90 Green	
		26-27		15 Yellow	

NOVA II 2x1, NOVA II 1x1

		28-29		30 Yellow	
		30-31		60 Yellow	
		32-33		90 Yellow	
		34-35		15 Red	
		36-37		30 Red	
		38-39		60 Red	
		40-41		90 Red	
		42-43		15 Magenta	
		44-45		30 Magenta	
		46-47		60 Magenta	
		48-49		90 Magenta	
		50-51		15 Pink	
		52-53		30 Pink	
		54-55		60 Pink	
		56-57		90 Pink	
		58-59		15 Lavender	
		60-61		30 Lavender	
		62-63		60 Lavender	
		64-65		90 Lavender	
		66-255		Reserved	
<b>GEL Category 3 : Rosco - Storaro</b>					
<b>6</b>		0-1		VS Red	
		2-3		VS Orange	
		4-5		VS Yellow	
		6-7		VS Green	
		8-9		VS Cyan	
		10-11		VS Azure	
		12-13		VS Blue	
		14-15		VS Indigo	
		16-17		VS Violet	
		18-19		VS Magenta	
		20-255		Reserved	
<b>GEL Category 4 : Rosco - Cinelux</b>					
<b>6</b>		0-1		Bastard Amber	

NOVA II 2x1, NOVA II 1x1

	2-3	Pale Bastard Amber
	4-5	No Color Straw
	6-7	Pale Gold
	8-9	Daffodil
	10-11	Straw
	12-13	Light Amber
	14-15	Gallo Gold
	16-17	Light Flame
	18-19	Flame
	20-21	Mayan Sun
	22-23	Golden Amber
	24-25	Soft Golden Amber
	26-27	Orange
	28-29	Henna Sky
	30-31	Light Red
	32-33	No Color Pink
	34-35	Blush Pink
	36-37	Flesh Pink
	38-39	Pale Rose Pink
	40-41	Salmon
	42-43	Deep Salmon
	44-45	Middle Rose
	46-47	Light Rose Purple
	48-49	Surprise Pink
	50-51	No Color Blue
	52-53	Clearwater
	54-55	Booster Blue
	56-57	Tipton Blue
	58-59	Blue Bell
	60-61	Daylight Blue
	62-63	Tharon Delft Blue
	64-65	Cerulean Blue
	66-67	Bermuda Blue
	68-69	Green Blue

NOVA II 2x1, NOVA II 1x1

		70-71		Alice Blue	
		72-73		Primary Blue	
		74-75		Baldassari Blue	
		76-77		Medium Blue	
		78-79		Pale Yellow Green	
		80-81		Light Green	
		82-83		Moss Green	
		84-85		Primary Green	
		86-87		Turquoise	
		88-89		Blue Green	
		90-91		Chocolate	
		92-255		Reserved	
<b>GEL Category 1 : LEE - Color Correction</b>					
<b>6</b>		0-1		Double CTB	
		2-3		Full CTB	
		4-5		3/4 CTB	
		6-7		1/2 CTB	
		8-9		1/4 CTB	
		10-11		1/8 CTB	
		12-13		Double CTO	
		14-15		Full CTO	
		16-17		3/4 CTO	
		18-19		1/2 CTO	
		20-21		1/4 CTO	
		22-23		1/8 CTO	
		24-25		1 1/2 CTB	
		26-27		1 1/2 CTO	
		28-29		Full CTS	
		30-31		1/2 CTS	
		32-33		1/4 CTS	
		34-35		1/8 CTS	
		36-37		Full CTO + .3 ND	
		38-39		Full CTO + .6 ND	
		40-41		L.C.T. Yellow (Y1)	

NOVA II 2x1, NOVA II 1x1

		42-43		White Flame Green	
		44-45		LEE Fluorescent Green	
		46-47		Super Correction L.C.T. Yellow	
		48-49		Super Correction W.F. Green	
		50-51		H.M.I. (to Tungsten)	
		52-53		C.I.D. (to Tungsten)	
		54-55		C.S.I. (to Tungsten)	
		56-57		LEE Fluorescent 5700 Kelvin	
		58-59		LEE Fluorescent 4300 Kelvin	
		60-61		LEE Fluorescent 3600 Kelvin	
		62-63		LEE Plus Green	
		64-65		1/2 Plus Green	
		66-67		1/4 Plus Green	
		68-69		1/8 Plus Green	
		70-71		LEE Minus Green	
		72-73		1/2 Minus Green	
		74-75		1/4 Minus Green	
		76-77		1/8 Minus Green	
		78-255		Reserved	
<b>GEL Category 2 : LEE - Color Filters</b>					
<b>6</b>		0-1		Rose Pink	
		2-3		Lavender Tint	
		4-5		Medium Bastard Amber	
		6-7		Pale Yellow	
		8-9		Dark Salmon	
		10-11		Pale Amber Gold	
		12-13		Medium Yellow	
		14-15		Straw Tint	
		16-17		Surprise Peach	
		18-19		Fire	

	20-21	Medium Amber
	22-23	Gold Amber
	24-25	Dark Amber
	26-27	Scarlet
	28-29	Sunset Red
	30-31	Bright Red
	32-33	Light Pink
	34-35	Medium Pink
	36-37	Dark Magenta
	38-39	Rose Purple
	40-41	Light Lavender
	42-43	Paler Lavender
	44-45	Lavender
	46-47	Mist Blue
	48-49	Pale Blue
	50-51	Sky Blue
	52-53	Evening Blue
	54-55	Just Blue
	56-57	Deeper Blue
	58-59	Lime Green
	60-61	Moss Green
	62-63	Dark Yellow Green
	64-65	Spring Yellow
	66-67	Yellow
	68-69	Light Amber
	70-71	Straw
	72-73	Deep Amber
	74-75	Primary Red
	76-77	Light Rose
	78-79	English Rose
	80-81	Light Salmon
	82-83	Middle Rose
	84-85	Dark Pink
	86-87	Magenta

NOVA II 2x1, NOVA II 1x1

	88-89	Peacock Blue
	90-91	Steel Blue
	92-93	Light Blue
	94-95	Deep Blue
	96-97	LEE Green
	98-99	Fern Green
	100-101	Dark Green
	102-103	Smokey Pink
	104-105	Bright Pink
	106-107	Marine Blue
	108-109	Golden Amber
	110-111	Deep Golden Amber
	112-113	Pale Lavender
	114-115	Special Lavender
	116-117	Pale Green
	118-119	Summer Blue
	120-121	Pale Violet
	122-123	Pale Navy Blue
	124-125	No Color Blue
	126-127	Apricot
	128-129	Bright Rose
	130-131	Gold Tint
	132-133	Pale Gold
	134-135	Pale Salmon
	136-137	Pale Rose
	138-139	Chocolate
	140-141	Pink
	142-143	No Color Straw
	144-145	Slate Blue
	146-147	Bastard Amber
	148-149	Flame Red
	150-151	Daylight Blue
	152-153	Lilac Tint
	154-155	Deep Lavender

NOVA II 2x1, NOVA II 1x1

		156-157		Dark Steel Blue	
		158-159		Loving Amber	
		160-161		Dark Lavender	
		162-163		Light Red	
		164-165		Flesh Pink	
		166-167		Surprise Pink	
		168-169		Zenith Blue	
		170-171		True Blue	
		172-173		Alice Blue	
		174-175		Palace Blue	
		176-177		Regal Blue	
		178-255		Reserved	
<b>GEL Category 3 : LEE - 600 Series</b>					
<b>6</b>		0-1		Arctic White	
		2-3		Silver	
		4-5		Platinum	
		6-7		Moonlight White	
		8-9		Full CT 85	
		10-11		Industry Sodium	
		12-13		HI Sodium	
		14-15		Urban Sodium	
		16-17		LO Sodium	
		18-255		Reserved	
<b>GEL Category 4 : LEE - Cosmetic Filters</b>					
<b>6</b>		0-1		Cosmetic Peach	
		2-3		Cosmetic Silver Rose	
		4-5		Cosmetic Rouge	
		6-7		Cosmetic Highlight	
		8-9		Cosmetic Silver Moss	
		10-11		Cosmetic Aqua Blue	
		12-13		Lily Frost	
		14-15		Shanklin Frost	
		16-17		Half Shanklin Frost	
		18-19		Durham Daylight Frost	

NOVA II 2x1, NOVA II 1x1

		20-21		Hampshire Rose	
		22-23		Durham Frost	
		24-25		Soft Amber Key 1	
		26-27		Soft Amber Key 2	
		28-29		Moroccan Frost	
		30-31		Blue Diffusion	
		32-33		Blue Frost	
		34-35		Daylight Blue Frost	
		36-255		Reserved	
<b>GEL Category 5 : LEE - 700 Series</b>					
<b>6</b>		0-1		Perfect Lavender	
		2-3		Provence	
		4-5		Special Pale Lavender	
		6-7		Cold Lavender	
		8-9		Lily	
		10-11		King Fals Lavender	
		12-13		Cool Lavender	
		14-15		Electric Lilac	
		16-17		Spir Special Blue	
		18-19		Cold Blue	
		20-21		Bedford Blue	
		22-23		Elysian Blue	
		24-25		Cabana Blue	
		26-27		Mikkel Blue	
		28-29		Colour Wash Blue	
		30-31		Berry Blue	
		32-33		Virgin Blue	
		34-35		Ocean Blue	
		36-37		Old Steel Blue	
		38-39		Steel Green	
	40-41		Liberty Green		
	42-43		Dirty Ice		
	44-45		Damp Squib		
	46-47		JAS Green		

NOVA II 2x1, NOVA II 1x1

		48-49		Bram Brown	
		50-51		Dirty White	
		52-53		Brown	
		54-55		Easy White	
		56-57		Seedy Pink	
		58-59		Wheat	
		60-61		Sun Colour Straw	
		62-63		LEE Yellow	
		64-65		Cardbox Amber	
		66-67		Nectarine	
		68-69		Millenium Gold	
		70-71		Bastard Pink	
		72-73		Terry Red	
		74-75		Blood Red	
		76-77		Moroccan Pink	
		78-79		Pretty n'Pink	
		80-81		Magical Magenta	
		82-255		Reserved	

# Control Channel Profiles - 1 Pixel

## DMX Control Channel Chart

The DMX Control Channel of the Profile should be a 0 value and then moved to the specific DMX Value to execute the command. Once executed, the DMX value should be returned to zero.

DMX			FUNCTION	DESCRIPTION	Time to Save
0	-	10	No function	Nothing	2.5 seconds
11	-	13	Signal Flash Enabled	When sending a Control Channel Command, the Light Flashes to confirm received	2.5 seconds
14	-	16	Signal Flash Disabled	When sending a Control Channel Command, the Light will not flash when a command is received.	2.5 seconds
17	-	19	Sidus BT On		2.5 seconds
20	-	22	Sidus BT Off		2.5 seconds
23	-	25	Sidus BT Reset		2.5 seconds
26	-	28	DMX Smoothing: Off	Snap to Intensities	2.5 seconds / Instant On
29	-	31	DMX Smoothing: Smooth	Smooth to Intensities	2.5 seconds / Instant On
32	-	34	DMX Smoothing: Super Smooth	Super Smooth to Intensities	2.5 seconds / Instant On
35	-	37	DMX Smoothing: Feather	Super Smooth from 0-4%, Snaps from 5 to 100%	2.5 seconds / Instant On
38	-	40	CRMX On	Turns wireless CRMX ON	2.5 seconds
41	-	43	CRMX Off	Turns wireless CRMX OFF	2.5 seconds
44	-	46	CRMX Unlink	TX: Unlink all linked fixtures RX: Unlink the fixture from a CRMX transmitter	2.5 seconds
47	-	49	CRMX Link	If set as a CRMX Transmitter, it will send the Link Signal	2.5 seconds
50	-	52	CRMX Mode RX	If set to a CRMX TX, it will change to RX. If it is off, it will remain off.	2.5 seconds

53	-	55	CRMX Mode TX	If set to a CRMX RX, it will change to TX. If it is off, it will remain off.	2.5 seconds
56	-	58	RDM off	Turns off the RDM	2.5 seconds
59	-	61	RDM on	Turns on the RDM	2.5 seconds
62	-	64	High Speed Mode On	if available	2.5 seconds
65	-	67	High Speed Mode Off	if available	2.5 seconds
68	-	70	Constant Output		2.5 seconds
71	-	73	Maximum Output		2.5 seconds
74	-	76	Studio Mode ON		2.5 seconds
77	-	79	Studio Mode OFF		2.5 seconds
80	-	82	Turn On Fan DMX Control Channel		2.5 seconds
83	-	85	Turn Off Fan DMX Control Channel	Sets Fan to Smart	2.5 seconds
86	-	88	N/A		
89	-	91	N/A		
92	-	94	N/A		
95	-	97	N/A		
98	-	100	Dim curve Linear	Dim curve Linear	2.5 seconds
101	-	103	Dim curve Exponential	Dim curve Exponential	2.5 seconds
104	-	106	Dim curve Logarithmic	Dim curve Logarithmic	2.5 seconds
107	-	109	Dim curve S-Curve	Dim curve S-Curve	2.5 seconds
110	-	172	N/A		2.5 seconds
173	-	175	with Diffuser Calibration	Calibrated with Diffuser	2.5 seconds
176	-	178	No Diffuser Calibration	Calibrated for use without Diffuser accessories	2.5 seconds
179	-	249	Reserved		
250	-	252	Turn On Control Channel	Defaults to On	2.5 seconds
253	-	255	Turn off Control Channel	Commands sent on the DMX Control Channel will be ignored.	2.5 seconds



## Profile 41: CCT & RGB & Control - 8-bit (10 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
5	Red	0 - 255	0 - 100	Red Intensity	100% / 255
6	Green	0 - 255	0 - 100	Green Intensity	100% / 255
7	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Control Channels</b>					
8	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
9	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
10	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	

				*Do not patch "No Effect" range into consoles
				# High Mode applies to the NOVA II 1x1 only

## Profile 42: CCT & RGB & Control - 16-bit (17 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
9 / 10	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
11 / 12	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
13 / 14	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Control Channels</b>					
15	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
16	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
17	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the	

				NOVA II 1x1 only
--	--	--	--	------------------

## Profile 43: CCT & RGB & FX & Control - 8-bit (20 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
5	Red	0 - 255	0 - 100	Red Intensity	100% / 255
6	Green	0 - 255	0 - 100	Green Intensity	100% / 255
7	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>FX</b>					
8	Crossfade 2	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
9	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Explosion	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Other Effects	0 - 69	0 - 27	Loop	
70 - 255		28 - 100	Stop		
10	Effect Selection	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	

NOVA II 2x1, NOVA II 1x1

		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
		150 - 255	61 - 100	Reserved	
<b>11</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>12</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>13</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0
<b>14</b>	<b>Effect Parameter 4</b>	0 - 255	0 - 100		0% / 0
<b>15</b>	<b>Effect Parameter 5</b>	0 - 255	0 - 100		0% / 0
<b>16</b>	<b>Effect Parameter 6</b>	0 - 255	0 - 100		0% / 0
<b>17</b>	<b>Effect Parameter 7</b>	0 - 255	0 - 100		0% / 0
<b>Control Channels</b>					
<b>18</b>	<b>Strobe</b>	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
<b>19</b>	<b>Control Channel</b>	0 - 255	0 - 100	See Control Channel Chart	

<b>20</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 44: CCT & RGB & FX & Control - 16-bit (32 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
9 / 10	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
11 / 12	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
13 / 14	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>FX</b>					
15	Crossfade 2	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
16	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Explosion	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Other Effects	0 - 69	0 - 27	Loop	
		70 - 255	28 - 100	Stop	
17	Effect Selection	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	

NOVA II 2x1, NOVA II 1x1

		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
		150 - 255	61 - 100	Reserved	
18	Effect Parameter 1	0 - 255	0 - 100	See Effect Chart	0% / 0
19	Effect Parameter 2	0 - 255	0 - 100		0% / 0
20	Effect Parameter 3	0 - 255	0 - 100		0% / 0
21	Effect Parameter 4	0 - 255	0 - 100		0% / 0
22	Effect Parameter 5	0 - 255	0 - 100		0% / 0
23	Effect Parameter 6	0 - 255	0 - 100		0% / 0
24	Effect Parameter 7	0 - 255	0 - 100		0% / 0
25	Effect Parameter 8	0 - 255	0 - 100		0% / 0
26	Effect Parameter 9	0 - 255	0 - 100		0% / 0
27	Effect Parameter 10	0 - 255	0 - 100		0% / 0
28	Effect Parameter 11	0 - 255	0 - 100		0% / 0

NOVA II 2x1, NOVA II 1x1

<b>29</b>	<b>Effect Parameter 12</b>	0 - 255	0 - 100		0% / 0
<b>Control Channels</b>					
<b>30</b>	<b>Strobe</b>	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
<b>31</b>	<b>Control Channel</b>	0 - 255	0 - 100	See Control Channel Chart	
<b>32</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
			# High Mode applies to the NOVA II 1x1 only		

## Profile 45: CCT & RGB & xy & Control - 8-bit (13 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
5	Red	0 - 255	0 - 100	Red Intensity	100% / 255
6	Green	0 - 255	0 - 100	Green Intensity	100% / 255
7	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
8	Crossfade 2	0 - 255	0 - 100	CCTRGB to xy	0
9	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
10	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>Control Channels</b>					
11	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
12	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
13	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	

NOVA II 2x1, NOVA II 1x1

		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 46: CCT & RGB & xy & Control - 16-bit (23 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
9 / 10	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
11 / 12	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
13 / 14	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
15 / 16	Crossfade 2	0 - 65535	0 - 100	CCTRGB to xy	0
17 / 18	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
19 / 20	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>Control Channels</b>					
21	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
22	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
23	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	

NOVA II 2x1, NOVA II 1x1

		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 47: CCT & RGB & xy & FX & Control - 8-bit (23 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
5	Red	0 - 255	0 - 100	Red Intensity	100% / 255
6	Green	0 - 255	0 - 100	Green Intensity	100% / 255
7	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
8	Crossfade 2	0 - 255	0 - 100	CCTRGB to xy	0% / 0
9	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
10	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>FX</b>					
11	Crossfade 3	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
12	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Explosion	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Other Effects	0 - 69	0 - 27	Loop	
70 - 255		28 - 100	Stop		
13	Effect Selection	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	

NOVA II 2x1, NOVA II 1x1

		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
		150 - 255	61 - 100	Reserved	
<b>14</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>15</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>16</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0
<b>17</b>	<b>Effect Parameter 4</b>	0 - 255	0 - 100		0% / 0
<b>18</b>	<b>Effect Parameter 5</b>	0 - 255	0 - 100		0% / 0
<b>19</b>	<b>Effect Parameter 6</b>	0 - 255	0 - 100		0% / 0
<b>20</b>	<b>Effect Parameter 7</b>	0 - 255	0 - 100		0% / 0
<b>Control Channels</b>					
<b>21</b>	<b>Strobe</b>	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
<b>22</b>	<b>Control Channel</b>	0 - 255	0 - 100	See Control Channel Chart	
<b>23</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	

NOVA II 2x1, NOVA II 1x1

		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 48: CCT & RGB & xy & FX & Control - 16-bit (38 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
9 / 10	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
11 / 12	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
13 / 14	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
15 / 16	Crossfade 2	0 - 65535	0 - 100	CCTRGB to xy	0% / 0
17 / 18	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
19 / 20	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>FX</b>					
21	Crossfade 3	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
22	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Explosion	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Other Effects	0 - 69	0 - 27	Loop	
70 - 255		28 - 100	Stop		
23	Effect Selection	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	

NOVA II 2x1, NOVA II 1x1

		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
		150 - 255	61 - 100	Reserved	
<b>24</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>25</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>26</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0
<b>27</b>	<b>Effect Parameter 4</b>	0 - 255	0 - 100		0% / 0
<b>28</b>	<b>Effect Parameter 5</b>	0 - 255	0 - 100		0% / 0
<b>29</b>	<b>Effect Parameter 6</b>	0 - 255	0 - 100		0% / 0
<b>30</b>	<b>Effect Parameter 7</b>	0 - 255	0 - 100		0% / 0
<b>31</b>	<b>Effect Parameter 8</b>	0 - 255	0 - 100		0% / 0
<b>32</b>	<b>Effect Parameter 9</b>	0 - 255	0 - 100		0% / 0
<b>33</b>	<b>Effect Parameter 10</b>	0 - 255	0 - 100		0% / 0
<b>34</b>	<b>Effect Parameter 11</b>	0 - 255	0 - 100		0% / 0
<b>35</b>	<b>Effect Parameter 12</b>	0 - 255	0 - 100		0% / 0
<b>Control Channels</b>					
<b>36</b>	<b>Strobe</b>	0 - 13	0 - 5	Off	0% / 0

NOVA II 2x1, NOVA II 1x1

		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
<b>37</b>	<b>Control Channel</b>	0 - 255	0 - 100	<b>See Control Channel Chart</b>	
<b>38</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
					*Do not patch "No Effect" range into consoles
				# High Mode applies to the NOVA II 1x1 only	

## Profile 49: HSI+ & Control - 8-bit (6 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>CCT is Locked at 6500K</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
3	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
<b>Control Channels</b>					
4	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
5	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
6	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 50: HSI+ & Control - 16-bit (9 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>CCT is Locked at 6500K</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
5 / 6	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
<b>Control Channels</b>					
7	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
8	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
9	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 51: HSIC+ & Control - 8-bit (8 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
5	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
<b>Control Channels</b>					
6	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
7	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
8	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

NOVA II 2x1, NOVA II 1x1



## Profile 52: HSIC+ & Control - 16-bit (13 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
9 / 10	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
<b>Control Channels</b>					
11	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
12	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
13	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

NOVA II 2x1, NOVA II 1x1



## Profile 53: HSIC+ & FX & Control - 8-bit (18 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
5	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
<b>FX</b>					
6	Crossfade	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
7	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Explosion	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Other Effects	0 - 69	0 - 27	Loop	
70 - 255		28 - 100	Stop		
8	Effect Selection	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	

NOVA II 2x1, NOVA II 1x1

		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
		150 - 255	61 - 100	Reserved	
<b>9</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>10</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>11</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0
<b>12</b>	<b>Effect Parameter 4</b>	0 - 255	0 - 100		0% / 0
<b>13</b>	<b>Effect Parameter 5</b>	0 - 255	0 - 100		0% / 0
<b>14</b>	<b>Effect Parameter 6</b>	0 - 255	0 - 100		0% / 0
<b>15</b>	<b>Effect Parameter 7</b>	0 - 255	0 - 100		0% / 0
<b>Control Channels</b>					
<b>16</b>	<b>Strobe</b>	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
<b>17</b>	<b>Control Channel</b>	0 - 255	0 - 100	See Control Channel Chart	
<b>18</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	

		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
			# High Mode applies to the NOVA II 1x1 only		

## Profile 54: HSIC+ & FX & Control - 16-bit (28 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
9 / 10	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
<b>FX</b>					
11	Crossfade	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
12	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Explosion	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Other Effects	0 - 69	0 - 27	Loop	
70 - 255		28 - 100	Stop		
13	Effect Selection	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	

		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
		150 - 255	61 - 100	Reserved	
<b>14</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>15</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>16</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0
<b>17</b>	<b>Effect Parameter 4</b>	0 - 255	0 - 100		0% / 0
<b>18</b>	<b>Effect Parameter 5</b>	0 - 255	0 - 100		0% / 0
<b>19</b>	<b>Effect Parameter 6</b>	0 - 255	0 - 100		0% / 0
<b>20</b>	<b>Effect Parameter 7</b>	0 - 255	0 - 100		0% / 0
<b>21</b>	<b>Effect Parameter 8</b>	0 - 255	0 - 100		0% / 0
<b>22</b>	<b>Effect Parameter 9</b>	0 - 255	0 - 100		0% / 0
<b>23</b>	<b>Effect Parameter 10</b>	0 - 255	0 - 100		0% / 0
<b>24</b>	<b>Effect Parameter 11</b>	0 - 255	0 - 100		0% / 0
<b>25</b>	<b>Effect Parameter 12</b>	0 - 255	0 - 100		0% / 0

NOVA II 2x1, NOVA II 1x1

Control Channels						
26	Strobe	0 - 13		0 - 5	Off	0% / 0
		14 - 128		6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255		51 - 100	Constant ( 0.4Hz -> 25Hz )	
27	Control Channel	0 - 255		0 - 100	See Control Channel Chart	
28	Fan Mode	0 - 38		0 - 15	Smart	0% / 0
		39 - 77		16 - 30	High	
			39 - 50	16 - 19	Max#	
			51 - 77	20 - 30	High#	
		78 - 115		31 - 45	Medium	
		116 - 153		46 - 60	Low	
		154 - 191		61 - 75	Delayed	
		192 - 255		76 - 100	Silent	
				*Do not patch "No Effect" range into consoles		
				# High Mode applies to the NOVA II 1x1 only		

## Profile 55: HSIC+ & xy & Control - 8-bit (11 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
5	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
6	Crossfade	0 - 255	0 - 100	HSIC+ to xy	0% / 0
7	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
8	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>Control Channels</b>					
9	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
10	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
11	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	

		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 56: HSIC+ & xy & Control - 16-bit (19 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
9 / 10	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
11 / 12	Crossfade	0 - 65535	0 - 100	HSIC+ to xy	0% / 0
13 / 14	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
15 / 16	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>Control Channels</b>					
17	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
18	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
19	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	

		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 57: HSIC+ & xy & FX & Control - 8-bit (21 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
5	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
6	Crossfade	0 - 255	0 - 100	HSIC+ to xy	0% / 0
7	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
8	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>FX</b>					
9	Crossfade 2	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
10	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Explosion	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Other Effects	0 - 69	0 - 27	Loop	
		70 - 255	28 - 100	Stop	
11	Effect Selection	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	

		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
		150 - 255	61 - 100	Reserved	
12	Effect Parameter 1	0 - 255	0 - 100	See Effect Chart	0% / 0
13	Effect Parameter 2	0 - 255	0 - 100		0% / 0
14	Effect Parameter 3	0 - 255	0 - 100		0% / 0
15	Effect Parameter 4	0 - 255	0 - 100		0% / 0
16	Effect Parameter 5	0 - 255	0 - 100		0% / 0
17	Effect Parameter 6	0 - 255	0 - 100		0% / 0
18	Effect Parameter 7	0 - 255	0 - 100		0% / 0
<b>Control Channels</b>					
19	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
20	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
21	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	

		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 58: HSIC+ & xy & FX & Control - 16-bit (34 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
9 / 10	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
11 / 12	Crossfade	0 - 65535	0 - 100	HSIC+ to xy	0% / 0
13 / 14	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
15 / 16	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>FX</b>					
17	Crossfade 2	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
18	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Explosion	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Other Effects	0 - 69	0 - 27	Loop	
70 - 255		28 - 100	Stop		
19	Effect Selection	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	

NOVA II 2x1, NOVA II 1x1

		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
		150 - 255	61 - 100	Reserved	
<b>20</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>21</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>22</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0
<b>23</b>	<b>Effect Parameter 4</b>	0 - 255	0 - 100		0% / 0
<b>24</b>	<b>Effect Parameter 5</b>	0 - 255	0 - 100		0% / 0
<b>25</b>	<b>Effect Parameter 6</b>	0 - 255	0 - 100		0% / 0
<b>26</b>	<b>Effect Parameter 7</b>	0 - 255	0 - 100		0% / 0
<b>27</b>	<b>Effect Parameter 8</b>	0 - 255	0 - 100		0% / 0
<b>28</b>	<b>Effect Parameter 9</b>	0 - 255	0 - 100		0% / 0
<b>29</b>	<b>Effect Parameter 10</b>	0 - 255	0 - 100		0% / 0
<b>30</b>	<b>Effect Parameter 11</b>	0 - 255	0 - 100		0% / 0
<b>31</b>	<b>Effect Parameter 12</b>	0 - 255	0 - 100		0% / 0
<b>Control Channels</b>					
<b>32</b>	<b>Strobe</b>	0 - 13	0 - 5	Off	0% / 0

NOVA II 2x1, NOVA II 1x1

		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
<b>33</b>	<b>Control Channel</b>	<b>0 - 255</b>	<b>0 - 100</b>	<b>See Control Channel Chart</b>	
<b>34</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

### Profile 59: xy & Control - 8-bit (6 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>1</b>	<b>Intensity</b>	0 - 255	0 - 100	0 - 100%	0% / 0
<b>2</b>	<b>x Coordinate</b>	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
<b>3</b>	<b>y Coordinate</b>	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>Control Channels</b>					
<b>4</b>	<b>Strobe</b>	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	

		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
<b>5</b>	<b>Control Channel</b>	0 - 255	0 - 100	See Control Channel Chart	
<b>6</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 60: xy & Control - 16-bit (9 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
5 / 6	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>Control Channels</b>					
7	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
8	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
9	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 61: RGB & Control - 8-bit (6 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>CCT is Locked at 6500K</b>					
1	Red	0 - 255	0 - 100	Red Intensity	100% / 255
2	Green	0 - 255	0 - 100	Green Intensity	100% / 255
3	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Control Channels</b>					
4	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
5	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
6	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 62: RGB & Control - 16-bit (9 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>CCT is Locked at 6500K</b>					
1 / 2	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
3 / 4	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
5 / 6	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Control Channels</b>					
7	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
8	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
9	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 63: iRGB & Control - 8-bit (7 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>CCT is Locked at 6500K</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	Red	0 - 255	0 - 100	Red Intensity	100% / 255
3	Green	0 - 255	0 - 100	Green Intensity	100% / 255
4	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Control Channels</b>					
5	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
6	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
7	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 64: iRGB & Control - 16-bit (11 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>CCT is Locked at 6500K</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
5 / 6	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
7 / 8	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Control Channels</b>					
9	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
10	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
11	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 65: RGBAL & Control - 8-bit (8 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Red	0 - 255	0 - 100	Red Intensity	100% / 255
2	Green	0 - 255	0 - 100	Green Intensity	100% / 255
3	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
4	Amber	0 - 255	0 - 100	Amber Intensity	100% / 255
5	Lime	0 - 255	0 - 100	Lime Intensity	100% / 255
<b>Control Channels</b>					
6	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
7	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
8	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 66: RGBAL & Control - 16-bit (13 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
3 / 4	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
5 / 6	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
7 / 8	Amber	0 - 65535	0 - 100	Amber Intensity	100% / 65535
9 / 10	Lime	0 - 65535	0 - 100	Lime Intensity	100% / 65535
<b>Control Channels</b>					
11	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
12	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
13	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 67: CCT+ & Control - 8-bit (6 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
<b>Control Channels</b>					
4	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
5	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
6	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 68: CCT+ & Control - 16-bit (9 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
<b>Control Channels</b>					
7	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
8	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
9	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 69: Source Mode & Control - 8-bit (7 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	Source	0 - 2	0 - 1	Tungsten Bulb	0% / 0
		3 - 5	2 - 3	Incandescent	
		6 - 8	4 - 5	Halogen	
		9 - 11	6 - 7	Antique Bulb	
		12 - 14	8 - 9	Warm Antique Bulb	
		15 - 17	10 - 11	Christmas Lights	
		18 - 20	12 - 13	Night Light	
		21 - 23	14 - 15	Infrared Heat Lamp	
		24 - 26	16 - 17	Grow Light	
		27 - 29	18 - 19	CFL Soft White	
		30 - 32	20 - 21	CFL Bright White	
		33 - 35	22 - 23	CFL Cool White	
		36 - 38	24 - 25	CFL Daylight	
		39 - 41	26 - 27	Cool White 1	
		42 - 44	28 - 29	Cool White 2	
		45 - 47	30 - 31	Cool White 3	
		48 - 50	32 - 33	Warm White	
		51 - 53	34 - 35	CFL Blacklight	
		54 - 56	36 - 37	HMI	
		57 - 59	38 - 39	High Pressure Sodium	
		60 - 62	40 - 41	Low Pressure Sodium	
63 - 65	42 - 43	Mercury Vapor			
66 - 68	44 - 45	Metal Halide			
69 - 71	46 - 47	Ceramic			
72 - 74	48 - 49	Carbon Arc			
75 - 77	50 - 51	Xenon			
78 - 80	52 - 53	Candle			
81 - 83	54 - 55	Gas Fire			
84 - 86	56 - 57	Sun Direct			
87 - 89	58 - 59	Sun Overcast			
90 - 92	60 - 61	Sun Blue Hour			

NOVA II 2x1, NOVA II 1x1

		93 - 95	62 - 63	Mobile Phone	
		96 - 98	64 - 65	Computer Monitor	
		99 - 101	66 - 67	Electroluminescence	
		102 - 104	68 - 69	Blow Torch	
		105 - 107	70 - 71	Road Flare	
		108 - 110	72 - 73	Amber Caution	
		111-113	74 - 75	Green Traffic Light	
		114 - 116	76 - 77	Yellow Traffic Light	
		117 - 119	78 - 79	Red Traffic Light	
		120 - 122	80 - 81	Blue Glow Stick	
		123 - 125	82 - 83	Green Glow Stick	
		126 - 128	84 - 85	Red Glow Stick	
		129 - 131	86 - 87	Yellow Glow Stick	
		132 - 134	88 - 89	Pink Glow Stick	
		135 - 137	90 - 91	Violet Glow Stick	
		138 - 255	92 - 100	RESERVED	
<b>3</b>	<b>x Coordinate</b>	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
<b>4</b>	<b>y Coordinate</b>	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>Control Channels</b>					
<b>5</b>	<b>Strobe</b>	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
<b>6</b>	<b>Control Channel</b>	0 - 255	0 - 100	See Control Channel Chart	
<b>7</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	

		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 70: Source Mode & Control - 16-bit (10 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3	Source	0 - 2	0 - 1	Tungsten Bulb	0% / 0
		3 - 5	2 - 3	Incandescent	
		6 - 8	4 - 5	Halogen	
		9 - 11	6 - 7	Antique Bulb	
		12 - 14	8 - 9	Warm Antique Bulb	
		15 - 17	10 - 11	Christmas Lights	
		18 - 20	12 - 13	Night Light	
		21 - 23	14 - 15	Infrared Heat Lamp	
		24 - 26	16 - 17	Grow Light	
		27 - 29	18 - 19	CFL Soft White	
		30 - 32	20 - 21	CFL Bright White	
		33 - 35	22 - 23	CFL Cool White	
		36 - 38	24 - 25	CFL Daylight	
		39 - 41	26 - 27	Cool White 1	
		42 - 44	28 - 29	Cool White 2	
		45 - 47	30 - 31	Cool White 3	
		48 - 50	32 - 33	Warm White	
		51 - 53	34 - 35	CFL Blacklight	
		54 - 56	36 - 37	HMI	
		57 - 59	38 - 39	High Pressure Sodium	
60 - 62	40 - 41	Low Pressure Sodium			
63 - 65	42 - 43	Mercury Vapor			
66 - 68	44 - 45	Metal Halide			
69 - 71	46 - 47	Ceramic			
72 - 74	48 - 49	Carbon Arc			
75 - 77	50 - 51	Xenon			
78 - 80	52 - 53	Candle			
81 - 83	54 - 55	Gas Fire			
84 - 86	56 - 57	Sun Direct			
87 - 89	58 - 59	Sun Overcast			
90 - 92	60 - 61	Sun Blue Hour			

NOVA II 2x1, NOVA II 1x1

		93 - 95	62 - 63	Mobile Phone	
		96 - 98	64 - 65	Computer Monitor	
		99 - 101	66 - 67	Electroluminescence	
		102 - 104	68 - 69	Blow Torch	
		105 - 107	70 - 71	Road Flare	
		108 - 110	72 - 73	Amber Caution	
		111-113	74 - 75	Green Traffic Light	
		114 - 116	76 - 77	Yellow Traffic Light	
		117 - 119	78 - 79	Red Traffic Light	
		120 - 122	80 - 81	Blue Glow Stick	
		123 - 125	82 - 83	Green Glow Stick	
		126 - 128	84 - 85	Red Glow Stick	
		129 - 131	86 - 87	Yellow Glow Stick	
		132 - 135	88 - 89	Pink Glow Stick	
		136 - 138	90 - 91	Violet Glow Stick	
		139 - 255	92 - 100	RESERVED	
<b>4 / 5</b>	<b>x Coordinate</b>	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
<b>6 / 7</b>	<b>y Coordinate</b>	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>Control Channels</b>					
<b>8</b>	<b>Strobe</b>	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
<b>9</b>	<b>Control Channel</b>	0 - 255	0 - 100	See Control Channel Chart	
<b>10</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	

NOVA II 2x1, NOVA II 1x1

		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 71: Legacy Gel & Control - 8-bit (8 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 126	0 - 50	3200K	3200K / 0
		127 - 255	51 - 100	5600K	
3	Rosco / Lee	0 - 29	0 - 12	Rosco	0% / 0
		30 - 59	13 - 24	Lee	
		60 - 255	25 - 100	Reserved	
4	Series	0 - 9	0 - 4	R-Col.corr / L-Col.Corr	0% / 0
		10 - 19	5 - 8	R-Cal Color / L-Cal. Filter	
		20 - 29	9 - 12	R-Storaro / L-600 Series	
		30 - 39	13 - 16	R-Cinelux / L-Cosmetic	
		40 - 49	17 - 20	R-reserved / L-700 Series	
		50 - 255	21 - 100	Reserved	
5	Category	0 - 255	0 - 100	See GEL Category Tables Below	0% / 0
<b>GEL Category 1 : Rosco - Color Correction</b>					
5		0-1		Full CTB	
		2-3		3/4 CTB	
		4-5		1/2 CTB	
		6-7		1/3 CTB	
		8-9		1/4 CTB	
		10-11		1/8 CTB	
		12-13		Double CTB	
		14-15		Full CTO	
		16-17		3/4 CTO	
		18-19		1/2 CTO	
		20-21		1/4 CTO	
		22-23		1/8 CTO	
		24-25		Double CTO	
	26-27		Full CTS		

NOVA II 2x1, NOVA II 1x1

		28-29		1/2 CTS	
		30-31		1/4 CTS	
		32-33		1/8 CTS	
		34-35		Full Plusgreen	
		36-37		1/2 Plusgreen	
		38-39		1/4 Plusgreen	
		40-41		1/8 Plusgreen	
		42-43		Full Minusgreen	
		44-45		3/4 Minusgreen	
		46-47		1/2 Minusgreen	
		48-49		1/4 Minusgreen	
		50-51		1/8 Minusgreen	
		52-53		Fluorofilter	
		54-55		Industrial Vapor	
		56-57		Urban Vapor	
		58-59		Tough Y1	
		60-61		Tough MT 54	
		62-63		Tough MTY	
		64-65		Tough MT2	
		66-255		Reserved	
<b>GEL Category 1 : Rosco - Cal Color</b>					
<b>5</b>		0-1		15 Blue	
		2-3		30 Blue	
		4-5		60 Blue	
		6-7		90 Blue	
		8-9		7 Cyan	
		10-11		15 Cyan	
		12-13		30 Cyan	
		14-15		60 Cyan	
		16-17		90 Cyan	
		18-19		15 Green	
		20-21		30 Green	
		22-23		60 Green	
		24-25		90 Green	

NOVA II 2x1, NOVA II 1x1

		26-27		15 Yellow	
		28-29		30 Yellow	
		30-31		60 Yellow	
		32-33		90 Yellow	
		34-35		15 Red	
		36-37		30 Red	
		38-39		60 Red	
		40-41		90 Red	
		42-43		15 Magenta	
		44-45		30 Magenta	
		46-47		60 Magenta	
		48-49		90 Magenta	
		50-51		15 Pink	
		52-53		30 Pink	
		54-55		60 Pink	
		56-57		90 Pink	
		58-59		15 Lavender	
		60-61		30 Lavender	
		62-63		60 Lavender	
		64-65		90 Lavender	
		66-255		Reserved	
<b>GEL Category 3 : Rosco - Storaro</b>					
<b>5</b>		0-1		VS Red	
		2-3		VS Orange	
		4-5		VS Yellow	
		6-7		VS Green	
		8-9		VS Cyan	
		10-11		VS Azure	
		12-13		VS Blue	
		14-15		VS Indigo	
		16-17		VS Violet	
		18-19		VS Magenta	
		20-255		Reserved	
<b>GEL Category 4 : Rosco - Cinelux</b>					

NOVA II 2x1, NOVA II 1x1

5		0-1		Bastard Amber
		2-3		Pale Bastard Amber
		4-5		No Color Straw
		6-7		Pale Gold
		8-9		Daffodil
		10-11		Straw
		12-13		Light Amber
		14-15		Gallo Gold
		16-17		Light Flame
		18-19		Flame
		20-21		Mayan Sun
		22-23		Golden Amber
		24-25		Soft Golden Amber
		26-27		Orange
		28-29		Henna Sky
		30-31		Light Red
		32-33		No Color Pink
		34-35		Blush Pink
		36-37		Flesh Pink
		38-39		Pale Rose Pink
		40-41		Salmon
		42-43		Deep Salmon
		44-45		Middle Rose
		46-47		Light Rose Purple
		48-49		Surprise Pink
		50-51		No Color Blue
		52-53		Clearwater
		54-55		Booster Blue
		56-57		Tipton Blue
		58-59		Blue Bell
		60-61		Daylight Blue
		62-63		Tharon Delft Blue
	64-65		Cerulean Blue	
	66-67		Bermuda Blue	

NOVA II 2x1, NOVA II 1x1

		68-69		Green Blue	
		70-71		Alice Blue	
		72-73		Primary Blue	
		74-75		Baldassari Blue	
		76-77		Medium Blue	
		78-79		Pale Yellow Green	
		80-81		Light Green	
		82-83		Moss Green	
		84-85		Primary Green	
		86-87		Turquoise	
		88-89		Blue Green	
		90-91		Chocolate	
		92-255		Reserved	
<b>GEL Category 1 : LEE - Color Correction</b>					
<b>5</b>		0-1		Double CTB	
		2-3		Full CTB	
		4-5		3/4 CTB	
		6-7		1/2 CTB	
		8-9		1/4 CTB	
		10-11		1/8 CTB	
		12-13		Double CTO	
		14-15		Full CTO	
		16-17		3/4 CTO	
		18-19		1/2 CTO	
		20-21		1/4 CTO	
		22-23		1/8 CTO	
		24-25		1 1/2 CTB	
		26-27		1 1/2 CTO	
		28-29		Full CTS	
		30-31		1/2 CTS	
		32-33		1/4 CTS	
		34-35		1/8 CTS	
		36-37		Full CTO + .3 ND	
	38-39		Full CTO + .6 ND		

NOVA II 2x1, NOVA II 1x1

		40-41		L.C.T. Yellow (Y1)	
		42-43		White Flame Green	
		44-45		LEE Fluorescent Green	
		46-47		Super Correction L.C.T. Yellow	
		48-49		Super Correction W.F. Green	
		50-51		H.M.I. (to Tungsten)	
		52-53		C.I.D. (to Tungsten)	
		54-55		C.S.I. (to Tungsten)	
		56-57		LEE Fluorescent 5700 Kelvin	
		58-59		LEE Fluorescent 4300 Kelvin	
		60-61		LEE Fluorescent 3600 Kelvin	
		62-63		LEE Plus Green	
		64-65		1/2 Plus Green	
		66-67		1/4 Plus Green	
		68-69		1/8 Plus Green	
		70-71		LEE Minus Green	
		72-73		1/2 Minus Green	
		74-75		1/4 Minus Green	
		76-77		1/8 Minus Green	
		78-255		Reserved	
<b>GEL Category 2 : LEE - Color Filters</b>					
<b>5</b>		0-1		Rose Pink	
		2-3		Lavender Tint	
		4-5		Medium Bastard Amber	
		6-7		Pale Yellow	
		8-9		Dark Salmon	
		10-11		Pale Amber Gold	
		12-13		Medium Yellow	
		14-15		Straw Tint	

NOVA II 2x1, NOVA II 1x1

	16-17		Surprise Peach
	18-19		Fire
	20-21		Medium Amber
	22-23		Gold Amber
	24-25		Dark Amber
	26-27		Scarlet
	28-29		Sunset Red
	30-31		Bright Red
	32-33		Light Pink
	34-35		Medium Pink
	36-37		Dark Magenta
	38-39		Rose Purple
	40-41		Light Lavender
	42-43		Paler Lavender
	44-45		Lavender
	46-47		Mist Blue
	48-49		Pale Blue
	50-51		Sky Blue
	52-53		Evening Blue
	54-55		Just Blue
	56-57		Deeper Blue
	58-59		Lime Green
	60-61		Moss Green
	62-63		Dark Yellow Green
	64-65		Spring Yellow
	66-67		Yellow
	68-69		Light Amber
	70-71		Straw
	72-73		Deep Amber
	74-75		Primary Red
	76-77		Light Rose
	78-79		English Rose
	80-81		Light Salmon
	82-83		Middle Rose

NOVA II 2x1, NOVA II 1x1

	84-85		Dark Pink
	86-87		Magenta
	88-89		Peacock Blue
	90-91		Steel Blue
	92-93		Light Blue
	94-95		Deep Blue
	96-97		LEE Green
	98-99		Fern Green
	100-101		Dark Green
	102-103		Smokey Pink
	104-105		Bright Pink
	106-107		Marine Blue
	108-109		Golden Amber
	110-111		Deep Golden Amber
	112-113		Pale Lavender
	114-115		Special Lavender
	116-117		Pale Green
	118-119		Summer Blue
	120-121		Pale Violet
	122-123		Pale Navy Blue
	124-125		No Color Blue
	126-127		Apricot
	128-129		Bright Rose
	130-131		Gold Tint
	132-133		Pale Gold
	134-135		Pale Salmon
	136-137		Pale Rose
	138-139		Chocolate
	140-141		Pink
	142-143		No Color Straw
	144-145		Slate Blue
	146-147		Bastard Amber
	148-149		Flame Red
	150-151		Daylight Blue

NOVA II 2x1, NOVA II 1x1

		152-153		Lilac Tint	
		154-155		Deep Lavender	
		156-157		Dark Steel Blue	
		158-159		Loving Amber	
		160-161		Dark Lavender	
		162-163		Light Red	
		164-165		Flesh Pink	
		166-167		Surprise Pink	
		168-169		Zenith Blue	
		170-171		True Blue	
		172-173		Alice Blue	
		174-175		Palace Blue	
		176-177		Regal Blue	
		178-255		Reserved	
<b>GEL Category 3 : LEE - 600 Series</b>					
<b>5</b>		0-1		Arctic White	
		2-3		Silver	
		4-5		Platinum	
		6-7		Moonlight White	
		8-9		Full CT 85	
		10-11		Industry Sodium	
		12-13		HI Sodium	
		14-15		Urban Sodium	
		16-17		LO Sodium	
		18-255		Reserved	
<b>GEL Category 4 : LEE - Cosmetic Filters</b>					
<b>5</b>		0-1		Cosmetic Peach	
		2-3		Cosmetic Silver Rose	
		4-5		Cosmetic Rouge	
		6-7		Cosmetic Highlight	
		8-9		Cosmetic Silver Moss	
		10-11		Cosmetic Aqua Blue	
		12-13		Lily Frost	
		14-15		Shanklin Frost	

NOVA II 2x1, NOVA II 1x1

		16-17		Half Shanklin Frost	
		18-19		Durham Daylight Frost	
		20-21		Hampshire Rose	
		22-23		Durham Frost	
		24-25		Soft Amber Key 1	
		26-27		Soft Amber Key 2	
		28-29		Moroccan Frost	
		30-31		Blue Diffusion	
		32-33		Blue Frost	
		34-35		Daylight Blue Frost	
		36-255		Reserved	
<b>GEL Category 5 : LEE - 700 Series</b>					
<b>5</b>		0-1		Perfect Lavender	
		2-3		Provence	
		4-5		Special Pale Lavender	
		6-7		Cold Lavender	
		8-9		Lily	
		10-11		King Fals Lavender	
		12-13		Cool Lavender	
		14-15		Electric Lilac	
		16-17		Spir Special Blue	
		18-19		Cold Blue	
		20-21		Bedford Blue	
		22-23		Elysian Blue	
		24-25		Cabana Blue	
		26-27		Mikkel Blue	
		28-29		Colour Wash Blue	
		30-31		Berry Blue	
		32-33		Virgin Blue	
		34-35		Ocean Blue	
		36-37		Old Steel Blue	
		38-39		Steel Green	
	40-41		Liberty Green		
	42-43		Dirty Ice		

NOVA II 2x1, NOVA II 1x1

		44-45		Damp Squib	
		46-47		JAS Green	
		48-49		Bram Brown	
		50-51		Dirty White	
		52-53		Brown	
		54-55		Easy White	
		56-57		Seedy Pink	
		58-59		Wheat	
		60-61		Sun Colour Straw	
		62-63		LEE Yellow	
		64-65		Cardbox Amber	
		66-67		Nectarine	
		68-69		Millenium Gold	
		70-71		Bastard Pink	
		72-73		Terry Red	
		74-75		Blood Red	
		76-77		Moroccan Pink	
		78-79		Pretty n'Pink	
		80-81		Magical Magenta	
		82-255		Reserved	
<b>Control Channels</b>					
<b>6</b>	<b>Strobe</b>	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
<b>7</b>	<b>Control Channel</b>	0 - 255	0 - 100	See Control Channel Chart	
<b>8</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	

		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

### **Profile 72: Legacy Gel & Control - 16-bit (9 ch.)**

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3	CCT	0 - 126	0 - 50	3200K	3200K / 0
		127 - 255	51 - 100	5600K	
4	Rosco / Lee	0 - 29	0 - 12	Rosco	0% / 0
		30 - 59	13 - 24	Lee	
		60 - 255	25 - 100	Reserved	
5	Series	0 - 9	0 - 4	R-Col.corr / L-Col.Corr	0% / 0
		10 - 19	5 - 8	R-Cal Color / L-Cal. Filter	
		20 - 29	9 - 12	R-Storaro / L-600 Series	
		30 - 39	13 - 16	R-Cinelux / L-Cosmetic	
		40 - 49	17 - 20	R-reserved / L-700 Series	
		50 - 255	21 - 100	Reserved	
6	Category	0 - 255	0 - 100	See GEL Category Tables Below	0% / 0
<b>GEL Category 1 : Rosco - Color Correction</b>					
6		0-1		Full CTB	
		2-3		3/4 CTB	
		4-5		1/2 CTB	
		6-7		1/3 CTB	
		8-9		1/4 CTB	

NOVA II 2x1, NOVA II 1x1

		10-11		1/8 CTB	
		12-13		Double CTB	
		14-15		Full CTO	
		16-17		3/4 CTO	
		18-19		1/2 CTO	
		20-21		1/4 CTO	
		22-23		1/8 CTO	
		24-25		Double CTO	
		26-27		Full CTS	
		28-29		1/2 CTS	
		30-31		1/4 CTS	
		32-33		1/8 CTS	
		34-35		Full Plusgreen	
		36-37		1/2 Plusgreen	
		38-39		1/4 Plusgreen	
		40-41		1/8 Plusgreen	
		42-43		Full Minusgreen	
		44-45		3/4 Minusgreen	
		46-47		1/2 Minusgreen	
		48-49		1/4 Minusgreen	
		50-51		1/8 Minusgreen	
		52-53		Fluorofilter	
		54-55		Industrial Vapor	
		56-57		Urban Vapor	
		58-59		Tough Y1	
		60-61		Tough MT 54	
		62-63		Tough MTY	
		64-65		Tough MT2	
		66-255		Reserved	
<b>GEL Category 1 : Rosco - Cal Color</b>					
<b>6</b>		0-1		15 Blue	
		2-3		30 Blue	
		4-5		60 Blue	
		6-7		90 Blue	

NOVA II 2x1, NOVA II 1x1

		8-9		7 Cyan	
		10-11		15 Cyan	
		12-13		30 Cyan	
		14-15		60 Cyan	
		16-17		90 Cyan	
		18-19		15 Green	
		20-21		30 Green	
		22-23		60 Green	
		24-25		90 Green	
		26-27		15 Yellow	
		28-29		30 Yellow	
		30-31		60 Yellow	
		32-33		90 Yellow	
		34-35		15 Red	
		36-37		30 Red	
		38-39		60 Red	
		40-41		90 Red	
		42-43		15 Magenta	
		44-45		30 Magenta	
		46-47		60 Magenta	
		48-49		90 Magenta	
		50-51		15 Pink	
		52-53		30 Pink	
		54-55		60 Pink	
		56-57		90 Pink	
		58-59		15 Lavender	
		60-61		30 Lavender	
		62-63		60 Lavender	
		64-65		90 Lavender	
		66-255		Reserved	
<b>GEL Category 3 : Rosco - Storaro</b>					
<b>6</b>		0-1		VS Red	
		2-3		VS Orange	
		4-5		VS Yellow	

NOVA II 2x1, NOVA II 1x1

		6-7		VS Green	
		8-9		VS Cyan	
		10-11		VS Azure	
		12-13		VS Blue	
		14-15		VS Indigo	
		16-17		VS Violet	
		18-19		VS Magenta	
		20-255		Reserved	
<b>GEL Category 4 : Rosco - Cinelux</b>					
<b>6</b>		0-1		Bastard Amber	
		2-3		Pale Bastard Amber	
		4-5		No Color Straw	
		6-7		Pale Gold	
		8-9		Daffodil	
		10-11		Straw	
		12-13		Light Amber	
		14-15		Gallo Gold	
		16-17		Light Flame	
		18-19		Flame	
		20-21		Mayan Sun	
		22-23		Golden Amber	
		24-25		Soft Golden Amber	
		26-27		Orange	
		28-29		Henna Sky	
		30-31		Light Red	
		32-33		No Color Pink	
		34-35		Blush Pink	
		36-37		Flesh Pink	
		38-39		Pale Rose Pink	
	40-41		Salmon		
	42-43		Deep Salmon		
	44-45		Middle Rose		
	46-47		Light Rose Purple		
	48-49		Surprise Pink		

NOVA II 2x1, NOVA II 1x1

		50-51		No Color Blue	
		52-53		Clearwater	
		54-55		Booster Blue	
		56-57		Tipton Blue	
		58-59		Blue Bell	
		60-61		Daylight Blue	
		62-63		Tharon Delft Blue	
		64-65		Cerulean Blue	
		66-67		Bermuda Blue	
		68-69		Green Blue	
		70-71		Alice Blue	
		72-73		Primary Blue	
		74-75		Baldassari Blue	
		76-77		Medium Blue	
		78-79		Pale Yellow Green	
		80-81		Light Green	
		82-83		Moss Green	
		84-85		Primary Green	
		86-87		Turquoise	
		88-89		Blue Green	
		90-91		Chocolate	
		92-255		Reserved	
<b>GEL Category 1 : LEE - Color Correction</b>					
<b>6</b>		0-1		Double CTB	
		2-3		Full CTB	
		4-5		3/4 CTB	
		6-7		1/2 CTB	
		8-9		1/4 CTB	
		10-11		1/8 CTB	
		12-13		Double CTO	
		14-15		Full CTO	
		16-17		3/4 CTO	
		18-19		1/2 CTO	
		20-21		1/4 CTO	

NOVA II 2x1, NOVA II 1x1

	22-23		1/8 CTO
	24-25		1 1/2 CTB
	26-27		1 1/2 CTO
	28-29		Full CTS
	30-31		1/2 CTS
	32-33		1/4 CTS
	34-35		1/8 CTS
	36-37		Full CTO + .3 ND
	38-39		Full CTO + .6 ND
	40-41		L.C.T. Yellow (Y1)
	42-43		White Flame Green
	44-45		LEE Fluorescent Green
	46-47		Super Correction L.C.T. Yellow
	48-49		Super Correction W.F. Green
	50-51		H.M.I. (to Tungsten)
	52-53		C.I.D. (to Tungsten)
	54-55		C.S.I. (to Tungsten)
	56-57		LEE Fluorescent 5700 Kelvin
	58-59		LEE Fluorescent 4300 Kelvin
	60-61		LEE Fluorescent 3600 Kelvin
	62-63		LEE Plus Green
	64-65		1/2 Plus Green
	66-67		1/4 Plus Green
	68-69		1/8 Plus Green
	70-71		LEE Minus Green
	72-73		1/2 Minus Green
	74-75		1/4 Minus Green
	76-77		1/8 Minus Green
	78-255		Reserved

GEL Category 2 : LEE - Color Filters				
6		0-1		Rose Pink
		2-3		Lavender Tint
		4-5		Medium Bastard Amber
		6-7		Pale Yellow
		8-9		Dark Salmon
		10-11		Pale Amber Gold
		12-13		Medium Yellow
		14-15		Straw Tint
		16-17		Surprise Peach
		18-19		Fire
		20-21		Medium Amber
		22-23		Gold Amber
		24-25		Dark Amber
		26-27		Scarlet
		28-29		Sunset Red
		30-31		Bright Red
		32-33		Light Pink
		34-35		Medium Pink
		36-37		Dark Magenta
		38-39		Rose Purple
		40-41		Light Lavender
		42-43		Paler Lavender
		44-45		Lavender
		46-47		Mist Blue
		48-49		Pale Blue
		50-51		Sky Blue
		52-53		Evening Blue
		54-55		Just Blue
		56-57		Deeper Blue
		58-59		Lime Green
		60-61		Moss Green
		62-63		Dark Yellow Green

NOVA II 2x1, NOVA II 1x1

	64-65		Spring Yellow
	66-67		Yellow
	68-69		Light Amber
	70-71		Straw
	72-73		Deep Amber
	74-75		Primary Red
	76-77		Light Rose
	78-79		English Rose
	80-81		Light Salmon
	82-83		Middle Rose
	84-85		Dark Pink
	86-87		Magenta
	88-89		Peacock Blue
	90-91		Steel Blue
	92-93		Light Blue
	94-95		Deep Blue
	96-97		LEE Green
	98-99		Fern Green
	100-101		Dark Green
	102-103		Smokey Pink
	104-105		Bright Pink
	106-107		Marine Blue
	108-109		Golden Amber
	110-111		Deep Golden Amber
	112-113		Pale Lavender
	114-115		Special Lavender
	116-117		Pale Green
	118-119		Summer Blue
	120-121		Pale Violet
	122-123		Pale Navy Blue
	124-125		No Color Blue
	126-127		Apricot
	128-129		Bright Rose
	130-131		Gold Tint

NOVA II 2x1, NOVA II 1x1

		132-133		Pale Gold	
		134-135		Pale Salmon	
		136-137		Pale Rose	
		138-139		Chocolate	
		140-141		Pink	
		142-143		No Color Straw	
		144-145		Slate Blue	
		146-147		Bastard Amber	
		148-149		Flame Red	
		150-151		Daylight Blue	
		152-153		Lilac Tint	
		154-155		Deep Lavender	
		156-157		Dark Steel Blue	
		158-159		Loving Amber	
		160-161		Dark Lavender	
		162-163		Light Red	
		164-165		Flesh Pink	
		166-167		Surprise Pink	
		168-169		Zenith Blue	
		170-171		True Blue	
		172-173		Alice Blue	
		174-175		Palace Blue	
		176-177		Regal Blue	
		178-255		Reserved	
<b>GEL Category 3 : LEE - 600 Series</b>					
<b>6</b>		0-1		Arctic White	
		2-3		Silver	
		4-5		Platinum	
		6-7		Moonlight White	
		8-9		Full CT 85	
		10-11		Industry Sodium	
		12-13		HI Sodium	
		14-15		Urban Sodium	
		16-17		LO Sodium	

NOVA II 2x1, NOVA II 1x1

		18-255		Reserved	
<b>GEL Category 4 : LEE - Cosmetic Filters</b>					
<b>6</b>		0-1		Cosmetic Peach	
		2-3		Cosmetic Silver Rose	
		4-5		Cosmetic Rouge	
		6-7		Cosmetic Highlight	
		8-9		Cosmetic Silver Moss	
		10-11		Cosmetic Aqua Blue	
		12-13		Lily Frost	
		14-15		Shanklin Frost	
		16-17		Half Shanklin Frost	
		18-19		Durham Daylight Frost	
		20-21		Hampshire Rose	
		22-23		Durham Frost	
		24-25		Soft Amber Key 1	
		26-27		Soft Amber Key 2	
		28-29		Moroccan Frost	
		30-31		Blue Diffusion	
		32-33		Blue Frost	
		34-35		Daylight Blue Frost	
	36-255		Reserved		
<b>GEL Category 5 : LEE - 700 Series</b>					
<b>6</b>		0-1		Perfect Lavender	
		2-3		Provence	
		4-5		Special Pale Lavender	
		6-7		Cold Lavender	
		8-9		Lily	
		10-11		King Fals Lavender	
		12-13		Cool Lavender	
		14-15		Electric Lilac	
		16-17		Spir Special Blue	
		18-19		Cold Blue	
		20-21		Bedford Blue	
		22-23		Elysian Blue	

NOVA II 2x1, NOVA II 1x1

		24-25		Cabana Blue	
		26-27		Mikkel Blue	
		28-29		Colour Wash Blue	
		30-31		Berry Blue	
		32-33		Virgin Blue	
		34-35		Ocean Blue	
		36-37		Old Steel Blue	
		38-39		Steel Green	
		40-41		Liberty Green	
		42-43		Dirty Ice	
		44-45		Damp Squib	
		46-47		JAS Green	
		48-49		Bram Brown	
		50-51		Dirty White	
		52-53		Brown	
		54-55		Easy White	
		56-57		Seedy Pink	
		58-59		Wheat	
		60-61		Sun Colour Straw	
		62-63		LEE Yellow	
		64-65		Cardbox Amber	
		66-67		Nectarine	
		68-69		Millenium Gold	
		70-71		Bastard Pink	
		72-73		Terry Red	
		74-75		Blood Red	
		76-77		Moroccan Pink	
		78-79		Pretty n'Pink	
		80-81		Magical Magenta	
		82-255		Reserved	
<b>Control Channels</b>					
<b>7</b>	<b>Strobe</b>	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	

NOVA II 2x1, NOVA II 1x1

		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )		
<b>8</b>	<b>Control Channel</b>	0 - 255	0 - 100	See Control Channel Chart		
<b>9</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0	
		39 - 77	16 - 30	High		
			39 - 50	16 - 19		Max#
			51 - 77	20 - 30		High#
		78 - 115	31 - 45	Medium		
		116 - 153	46 - 60	Low		
		154 - 191	61 - 75	Delayed		
		192 - 255	76 - 100	Silent		
				# High Mode applies to the NOVA II 1x1 only		

## Color Space Profiles - 1 Pixel

### Profile 81: VRGB & Control - 8-bit (9 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX	
1	Red	0 - 255	0 - 100	Red Intensity	100% / 255	
2	Green	0 - 255	0 - 100	Green Intensity	100% / 255	
3	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255	
4	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20	
5	±Green	0 - 10	0 - 4	Neutral / No Effect*	Neutral / 137	
		11 - 20	5 - 8	Full Minus Green		
		21 - 119	9 - 47	-99% - -1%		
		120 - 145	48 - 57	Neutral		
		146 - 244	58 - 96	1% - 99%		
		245 - 255	97 - 100	Full Plus Green		
6	Color Space	0 - 255	0 - 100	SEE COLOR SPACE CHART		
<b>Control Channels</b>						
7	Strobe	0 - 13	0 - 5	Off	0% / 0	
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )		
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )		
8	Control Channel	0 - 255	0 - 100	See Control Channel Chart		
9	Fan Mode	0 - 38	0 - 15	Smart	0% / 0	
		39 - 77	16 - 30	High		
			39 - 50	16 - 19		Max#
			51 - 77	20 - 30		High#
		78 - 115	31 - 45	Medium		
		116 - 153	46 - 60	Low		
		154 - 191	61 - 75	Delayed		
		192 - 255	76 - 100	Silent		

NOVA II 2x1, NOVA II 1x1

				*Do not patch "No Effect" range into consoles
				# High Mode applies to the NOVA II 1x1 only

### Profile 82: VRGB & Control - 16-bit (14 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
3 / 4	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
5 / 6	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
7 / 8	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
9 / 10	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
11	Color Space	0 - 255	0 - 100	SEE COLOR SPACE CHART	
<b>Control Channels</b>					
12	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
13	Control Channel	0 - 255	0 - 100	See Control Channel Chart	

NOVA II 2x1, NOVA II 1x1

<b>14</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 83: VRGB-I & Control - 8-bit (10 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Red	0 - 255	0 - 100	Red Intensity	100% / 255
2	Green	0 - 255	0 - 100	Green Intensity	100% / 255
3	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
4	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
5	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20 Neutral / 137
6	±Green	0 - 10	0 - 4	Neutral / No Effect*	
		11 - 20	5 - 8	Full Minus Green	
		21 - 119	9 - 47	-99% - -1%	
		120 - 145	48 - 57	Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	Full Plus Green	
7	Color Space	0 - 255	0 - 100	SEE COLOR SPACE CHART	
<b>Control Channels</b>					
8	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
9	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
10	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	

				# High Mode applies to the NOVA II 1x1 only
--	--	--	--	--

## Profile 84: VRGB & Control - 16-bit (16 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
3 / 4	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
5 / 6	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
7 / 8	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
9 / 10	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
11 / 12	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
13	Color Space	0 - 255	0 - 100	SEE COLOR SPACE CHART	
<b>Control Channels</b>					
14	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
15	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
16	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	

NOVA II 2x1, NOVA II 1x1

		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 85: VRGB-CS & Control - 8-bit (7 ch.)

CCT Locked at 6500K					
Channel	Function	Value	Percent	Description	Default % / DMX
1	Red	0 - 255	0 - 100	Red Intensity	100% / 255
2	Green	0 - 255	0 - 100	Green Intensity	100% / 255
3	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
4	Color Space	0 - 255	0 - 100	SEE COLOR SPACE CHART	
Control Channels					
5	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
6	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
7	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 86: VRGB-CS & Control - 16-bit (10 ch.)

CCT Locked at 6500K					
Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
3 / 4	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
5 / 6	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
7	Color Space	0 - 255	0 - 100	SEE COLOR SPACE CHART	
Control Channels					
8	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
9	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
10	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 87: VRGB-709 & Control - 8-bit (6 ch.)

CCT Locked at 6500K @ SRGB					
Channel	Function	Value	Percent	Description	Default % / DMX
1	Red	0 - 255	0 - 100	Red Intensity	100% / 255
2	Green	0 - 255	0 - 100	Green Intensity	100% / 255
3	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
Control Channels					
4	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
5	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
6	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 88: VRGB-709 & Control - 16-bit (9 ch.)

CCT Locked at 6500K @ SRGB

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
3 / 4	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
5 / 6	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
Control Channels					
7	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
8	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
9	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 89: VRGB-sRGB - 8-bit (6 ch.)

CCT Locked at 6500K @ SRGB

Channel	Function	Value	Percent	Description	Default % / DMX
1	Red	0 - 255	0 - 100	Red Intensity	100% / 255
2	Green	0 - 255	0 - 100	Green Intensity	100% / 255
3	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
Control Channels					
4	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
5	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
6	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 90: VRGB-sRGB - 16-bit (9 ch.)

CCT Locked at 6500K @ SRGB

Channel	Function	Value	Percent	Description	Default % / DMX
1 / 2	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
3 / 4	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
5 / 6	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
Control Channels					
7	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
8	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
9	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

# Color Space Chart

Value	Percent	Description	EOTF	RGB->XYZ Matrix
Default % / DMX 100% / 255				
0-255	0-100			
0 - 10	0 - 4	<b>Broadcast SDR</b>	<b>Gamma 2.4</b>	<b>Rec709</b>
11 - 20	5 - 8	<b>sRGB</b>	<b>sRGB</b>	<b>Rec709</b>
21 - 30	9 - 12	Broadcast Rec709 HDR (relative)	ST2084 (PQ) (Relative)	Rec709
31 - 40	13 - 16	Broadcast Rec709 HDR (1000 nits Scaled)	ST2084 1000 nits Scaled (relative)	Rec709
41 - 50	17 - 20	Broadcast HDR: HLG (Relative)	HLG 1200 nits Scaled (Relative)	Rec709
51 - 60	21 - 24	<b>Display P3</b>	<b>sRGB</b>	<b>P3 D65</b>
61 - 70	25 - 28	P3 HDR (relative)	ST2084 (PQ) (Relative)	P3 D65
71 - 80	29 - 32	<b>P3 HDR (1000 nits Scaled)</b>	<b>ST2084 1000 nits Scaled (relative)</b>	<b>P3 D65</b>
81 - 90	33 - 35	<b>P3 HDR: HLG (Relative)</b>	<b>HLG 1200 nits Scaled (Relative)</b>	<b>P3 D65</b>
91 - 100	36 - 39	Rec2020 SDR	Gamma 2.4	Rec2020
101 - 110	40 - 43	Rec2100 HDR (Relative)	ST2084 (PQ) (Relative)	Rec2020
111 - 120	44 - 47	<b>Rec2100 HDR (1000 nits Scaled)</b>	<b>ST2084 1000 nits Scaled (relative)</b>	Rec2020
121 - 130	48 - 51	<b>Rec2100 HDR: HLG (Relative)</b>	<b>HLG 1200 nits Scaled (Relative)</b>	Rec2020
131 - 140	52 - 55	Apple Log	Apple Log	Rec2020
141 - 150	56 - 59	ACES AP1 (relative)	ACEScct (relative)	ACES AP1
151 - 160	60 - 63	<b>ACES AP0</b>	<b>Linear</b>	<b>ACES AP0</b>
161 - 244	64 - 96	RESERVED	RESERVED	RESERVED
245 - 255	97 - 100	<b>Aputure Color Space</b>	<b>Linear</b>	<b>Aputure Gamut</b>

NOVA II 2x1, NOVA II 1x1

# Light Engine Profile (NOVA II 2x1 only)

## Basic DMX Profiles - 2 Pixels

### Profile 101: LE CCT & RGB - 8-bit - 2 Pixels (14 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
5	Red	0 - 255	0 - 100	Red Intensity	100% / 255
6	Green	0 - 255	0 - 100	Green Intensity	100% / 255
7	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Pixel 2</b>					
8	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
9	CCT	0 - 255	0 - 100	1800K to 20000K	3200K / 20
10	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
11	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
12	Red	0 - 255	0 - 100	Red Intensity	100% / 255
13	Green	0 - 255	0 - 100	Green Intensity	100% / 255

NOVA II 2x1, NOVA II 1x1

<b>14</b>	<b>Blue</b>	0 - 255	0 - 100	Blue Intensity	100% / 255
				*Do not patch "No Effect" range into consoles	

## Profile 102: LE CCT & RGB - 16-bit - 2 Pixels (28 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
9 / 10	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
11 / 12	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
13 / 14	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Pixel 2</b>					
15 / 16	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
17 / 18	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
19 / 20	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
21 / 22	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
23 / 24	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
25 / 26	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
27 / 28	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
				*Do not patch "No Effect" range into consoles	

## Profile 103: LE CCT & RGB & FX - 8-bit - 2 Pixels (24 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
5	Red	0 - 255	0 - 100	Red Intensity	100% / 255
6	Green	0 - 255	0 - 100	Green Intensity	100% / 255
7	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Pixel 2</b>					
8	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
9	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
10	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
11	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
12	Red	0 - 255	0 - 100	Red Intensity	100% / 255
13	Green	0 - 255	0 - 100	Green Intensity	100% / 255
14	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>FX</b>					
15	Crossfade 2	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
16	Trigger	0 - 9	0 - 4	Loop	0% / 0

NOVA II 2x1, NOVA II 1x1

		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	<b>Trigger Explosion</b>	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	<b>Trigger Other Effects</b>	0 - 69	0 - 27	Loop	
		70 - 255	28 - 100	Stop	
<b>17</b>	<b>Effect Selection</b>	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
		150 - 255	61 - 100	Reserved	
<b>18</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>19</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>20</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0
<b>21</b>	<b>Effect Parameter 4</b>	0 - 255	0 - 100		0% / 0
<b>22</b>	<b>Effect Parameter 5</b>	0 - 255	0 - 100		0% / 0
<b>23</b>	<b>Effect Parameter 6</b>	0 - 255	0 - 100		0% / 0
<b>24</b>	<b>Effect Parameter 7</b>	0 - 255	0 - 100		0% / 0

NOVA II 2x1, NOVA II 1x1

				*Do not patch "No Effect" range into consoles
--	--	--	--	---

### Profile 104: LE CCT & RGB & FX - 16-bit - 2 Pixels (43 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
62915 - 65535	97 - 100	100% / Full Plus Green			
7 / 8	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
9 / 10	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
11 / 12	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
13 / 14	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Pixel 2</b>					
15 / 16	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
17 / 18	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
19 / 20	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	

		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
<b>21 / 22</b>	<b>Crossfade</b>	0 - 65535	0 - 100	White Light to RGB	0% / 0
<b>23 / 24</b>	<b>Red</b>	0 - 65535	0 - 100	Red Intensity	100% / 65535
<b>25 / 26</b>	<b>Green</b>	0 - 65535	0 - 100	Green Intensity	100% / 65535
<b>27 / 28</b>	<b>Blue</b>	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>FX</b>					
<b>29</b>	<b>Crossfade 2</b>	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
<b>30</b>	<b>Trigger</b>	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	<b>Trigger Explosion</b>	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
		<b>Trigger Other Effects</b>	0 - 69	0 - 27	
70 - 255	28 - 100		Stop		
<b>31</b>	<b>Effect Selection</b>	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
		150 - 255	61 - 100	Reserved	
<b>32</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0

33	Effect Parameter 2	0 - 255	0 - 100		0% / 0
34	Effect Parameter 3	0 - 255	0 - 100		0% / 0
35	Effect Parameter 4	0 - 255	0 - 100		0% / 0
36	Effect Parameter 5	0 - 255	0 - 100		0% / 0
37	Effect Parameter 6	0 - 255	0 - 100		0% / 0
38	Effect Parameter 7	0 - 255	0 - 100		0% / 0
39	Effect Parameter 8	0 - 255	0 - 100		0% / 0
40	Effect Parameter 9	0 - 255	0 - 100		0% / 0
41	Effect Parameter 10	0 - 255	0 - 100		0% / 0
42	Effect Parameter 11	0 - 255	0 - 100		0% / 0
43	Effect Parameter 12	0 - 255	0 - 100		0% / 0
					*Do not patch "No Effect" range into consoles

## Profile 105: LE CCT & RGB & xy - 8-bit - 2 Pixels (20 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
5	Red	0 - 255	0 - 100	Red Intensity	100% / 255
6	Green	0 - 255	0 - 100	Green Intensity	100% / 255
7	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
8	Crossfade 2	0 - 255	0 - 100	CCTRGB to xy	0% / 0
9	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
10	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>Pixel 2</b>					
11	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
12	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
13	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
14	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
15	Red	0 - 255	0 - 100	Red Intensity	100% / 255
16	Green	0 - 255	0 - 100	Green Intensity	100% / 255
17	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255

NOVA II 2x1, NOVA II 1x1

<b>18</b>	<b>Crossfade 2</b>	0 - 255	0 - 100	CCTRGB to xy	0% / 0
<b>19</b>	<b>x Coordinate</b>	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
<b>20</b>	<b>y Coordinate</b>	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
				*Do not patch "No Effect" range into consoles	

## Profile 106: LE CCT & RGB & xy - 16-bit - 2 Pixels (40 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
9 / 10	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
11 / 12	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
13 / 14	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
15 / 16	Crossfade 2	0 - 65535	0 - 100	CCTRGB to xy	0% / 0
17 / 18	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
19 / 20	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>Pixel 2</b>					
21 / 22	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
23 / 24	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
25 / 26	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
27 / 28	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
29 / 30	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
31 / 32	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
33 / 34	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535

NOVA II 2x1, NOVA II 1x1

<b>35 / 36</b>	<b>Crossfade 2</b>	0 - 65535	0 - 100	CCTRGB to xy	0% / 0
<b>37 / 38</b>	<b>x Coordinate</b>	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
<b>39 / 40</b>	<b>y Coordinate</b>	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
				*Do not patch "No Effect" range into consoles	

## Profile 107: LE CCT & RGB & xy & FX - 8-bit - 2 Pixels (30 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
5	Red	0 - 255	0 - 100	Red Intensity	100% / 255
6	Green	0 - 255	0 - 100	Green Intensity	100% / 255
7	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
8	Crossfade 2	0 - 255	0 - 100	CCTRGB to xy	0% / 0
9	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
10	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>Pixel 2</b>					
11	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
12	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
13	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
14	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
15	Red	0 - 255	0 - 100	Red Intensity	100% / 255
16	Green	0 - 255	0 - 100	Green Intensity	100% / 255
17	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255

NOVA II 2x1, NOVA II 1x1

<b>18</b>	<b>Crossfade 2</b>	0 - 255	0 - 100	CCTRGB to xy	0% / 0
<b>19</b>	<b>x Coordinate</b>	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
<b>20</b>	<b>y Coordinate</b>	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>FX</b>					
<b>21</b>	<b>Crossfade 3</b>	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
<b>22</b>	<b>Trigger</b>	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	<b>Trigger Explosion</b>	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	<b>Trigger Other Effects</b>	0 - 69	0 - 27	Loop	
70 - 255		28 - 100	Stop		
<b>23</b>	<b>Effect Selection</b>	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
		150 - 255	61 - 100	Reserved	
<b>24</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>25</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>26</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0

<b>27</b>	<b>Effect Parameter 4</b>	0 - 255	0 - 100		0% / 0
<b>28</b>	<b>Effect Parameter 5</b>	0 - 255	0 - 100		0% / 0
<b>29</b>	<b>Effect Parameter 6</b>	0 - 255	0 - 100		0% / 0
<b>30</b>	<b>Effect Parameter 7</b>	0 - 255	0 - 100		0% / 0
				*Do not patch "No Effect" range into consoles	

## Profile 108: LE CCT & RGB & xy & FX - 16-bit - 2 Pixels (55 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
9 / 10	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
11 / 12	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
13 / 14	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
15 / 16	Crossfade 2	0 - 65535	0 - 100	CCTRGB to xy	0% / 0
17 / 18	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
19 / 20	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>Pixel 2</b>					
21 / 22	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
23 / 24	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
25 / 26	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
27 / 28	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
29 / 30	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
31 / 32	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
33 / 34	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535

NOVA II 2x1, NOVA II 1x1

<b>35 / 36</b>	<b>Crossfade 2</b>	0 - 65535	0 - 100	CCTRGB to xy	0% / 0
<b>37 / 38</b>	<b>x Coordinate</b>	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
<b>39 / 40</b>	<b>y Coordinate</b>	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>FX</b>					
<b>41</b>	<b>Crossfade 3</b>	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
<b>42</b>	<b>Trigger</b>	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	<b>Trigger Explosion</b>	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
		<b>Trigger Other Effects</b>	0 - 69	0 - 27	
70 - 255	28 - 100		Stop		
<b>43</b>	<b>Effect Selection</b>	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
150 - 255	61 - 100	Reserved			
<b>44</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>45</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>46</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0

47	Effect Parameter 4	0 - 255	0 - 100		0% / 0
48	Effect Parameter 5	0 - 255	0 - 100		0% / 0
49	Effect Parameter 6	0 - 255	0 - 100		0% / 0
50	Effect Parameter 7	0 - 255	0 - 100		0% / 0
51	Effect Parameter 8	0 - 255	0 - 100		0% / 0
52	Effect Parameter 9	0 - 255	0 - 100		0% / 0
53	Effect Parameter 10	0 - 255	0 - 100		0% / 0
54	Effect Parameter 11	0 - 255	0 - 100		0% / 0
55	Effect Parameter 12	0 - 255	0 - 100		0% / 0
					*Do not patch "No Effect" range into consoles

### Profile 109: LE HSI - 8-bit - 2 Pixels (6 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
CCT is Locked at 6500K					
Pixel 1					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
3	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
Pixel 2					
4	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
5	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
6	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0

### Profile 110: LE HSI - 16-bit - 2 Pixels (12 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
CCT is Locked at 6500K					
Pixel 1					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
5 / 6	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
Pixel 2					
7 / 8	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
9 / 10	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
11 / 12	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0

## Profile 111: LE HSIC+ - 8-bit - 2 Pixels (10 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
<b>1</b>	<b>Intensity</b>	0 - 255	0 - 100	0 - 100%	0% / 0
<b>2</b>	<b>CCT</b>	0 - 255	0 - 100	1800K - 20000K	3200K / 20
<b>3</b>	<b>±Green</b>	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
<b>4</b>	<b>Hue</b>	0 - 255	0 - 100	0 to 359.9°	0% / 0
<b>5</b>	<b>Saturation</b>	0 - 255	0 - 100	White Light to RGB	0% / 0
<b>Pixel 2</b>					
<b>6</b>	<b>Intensity</b>	0 - 255	0 - 100	0 - 100%	0% / 0
<b>7</b>	<b>CCT</b>	0 - 255	0 - 100	1800K - 20000K	3200K / 20
<b>8</b>	<b>±Green</b>	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
<b>9</b>	<b>Hue</b>	0 - 255	0 - 100	0 to 359.9°	0% / 0
<b>10</b>	<b>Saturation</b>	0 - 255	0 - 100	White Light to RGB	0% / 0
				*Do not patch "No Effect" range into consoles	

## Profile 112: LE HSIC+ - 16-bit - 2 Pixels (20 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
9 / 10	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
<b>Pixel 2</b>					
11 / 12	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
13 / 14	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
15 / 16	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
17 / 18	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
19 / 20	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
				*Do not patch "No Effect" range into consoles	

## Profile 113: LE HSIC+ & FX - 8-bit - 2 Pixels (20 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
5	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
<b>Pixel 2</b>					
6	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
7	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
8	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
9	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
10	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
<b>FX</b>					
11	Crossfade	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
12	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Explosion	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	

NOVA II 2x1, NOVA II 1x1

	<b>Trigger Other Effects</b>	0 - 69	0 - 27	Loop	
		70 - 255	28 - 100	Stop	
<b>13</b>	<b>Effect Selection</b>	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
			150 - 255	61 - 100	
<b>14</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>15</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>16</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0
<b>17</b>	<b>Effect Parameter 4</b>	0 - 255	0 - 100		0% / 0
<b>18</b>	<b>Effect Parameter 5</b>	0 - 255	0 - 100		0% / 0
<b>19</b>	<b>Effect Parameter 6</b>	0 - 255	0 - 100		0% / 0
<b>20</b>	<b>Effect Parameter 7</b>	0 - 255	0 - 100		0% / 0
					*Do not patch "No Effect" range into consoles

## Profile 114: LE HSIC+ & FX - 16-bit - 2 Pixels (35 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	<b>Intensity</b>	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	<b>CCT</b>	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	<b>±Green</b>	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	<b>Hue</b>	0 - 65535	0 - 100	0 to 359.9°	0% / 0
9 / 10	<b>Saturation</b>	0 - 65535	0 - 100	White Light to RGB	0% / 0
<b>Pixel 2</b>					
11 / 12	<b>Intensity</b>	0 - 65535	0 - 100	0 - 100%	0% / 0
13 / 14	<b>CCT</b>	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
15 / 16	<b>±Green</b>	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
17 / 18	<b>Hue</b>	0 - 65535	0 - 100	0 to 359.9°	0% / 0
19 / 20	<b>Saturation</b>	0 - 65535	0 - 100	White Light to RGB	0% / 0
<b>FX</b>					
21	<b>Crossfade</b>	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
22	<b>Trigger</b>	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	<b>Trigger Explosion</b>	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	

NOVA II 2x1, NOVA II 1x1

	<b>Trigger Other Effects</b>	0 - 69	0 - 27	Loop	
		70 - 255	28 - 100	Stop	
<b>23</b>	<b>Effect Selection</b>	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
			150 - 255	61 - 100	
<b>24</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>25</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>26</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0
<b>27</b>	<b>Effect Parameter 4</b>	0 - 255	0 - 100		0% / 0
<b>28</b>	<b>Effect Parameter 5</b>	0 - 255	0 - 100		0% / 0
<b>29</b>	<b>Effect Parameter 6</b>	0 - 255	0 - 100		0% / 0
<b>30</b>	<b>Effect Parameter 7</b>	0 - 255	0 - 100		0% / 0
<b>31</b>	<b>Effect Parameter 8</b>	0 - 255	0 - 100		0% / 0
<b>32</b>	<b>Effect Parameter 9</b>	0 - 255	0 - 100		0% / 0

<b>33</b>	<b>Effect Parameter 10</b>	0 - 255	0 - 100		0% / 0
<b>34</b>	<b>Effect Parameter 11</b>	0 - 255	0 - 100		0% / 0
<b>35</b>	<b>Effect Parameter 12</b>	0 - 255	0 - 100		0% / 0
				*Do not patch "No Effect" range into consoles	

## Profile 115: LE HSIC+ & xy - 8-bit - 2 Pixels (16 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
5	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
6	Crossfade	0 - 255	0 - 100	HSIC+ to xy	0% / 0
7	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
8	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>Pixel 2</b>					
9	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
10	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
11	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
12	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
13	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
14	Crossfade	0 - 255	0 - 100	HSIC+ to xy	0% / 0
15	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
16	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
				*Do not patch "No Effect" range into consoles	

## Profile 116: LE HSIC+ & xy - 16-bit - 2 Pixels (32 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
62915 - 65535	97 - 100	100% / Full Plus Green			
7 / 8	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
9 / 10	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
11 / 12	Crossfade	0 - 65535	0 - 100	HSIC+ to xy	0% / 0
13 / 14	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
15 / 16	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>Pixel 2</b>					
17 / 18	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
19 / 20	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
21 / 22	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
62915 - 65535	97 - 100	100% / Full Plus Green			
23 / 24	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
25 / 26	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
27 / 28	Crossfade	0 - 65535	0 - 100	HSIC+ to xy	0% / 0
29 / 30	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
31 / 32	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
				*Do not patch "No Effect" range into consoles	

## Profile 117: LE HSIC+ & xy & FX - 8-bit - 2 Pixels (26 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
5	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
6	Crossfade	0 - 255	0 - 100	HSIC+ to xy	0% / 0
7	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
8	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>Pixel 2</b>					
9	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
10	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
11	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
12	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
13	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
14	Crossfade	0 - 255	0 - 100	HSIC+ to xy	0% / 0
15	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
16	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>FX</b>					
17	Crossfade 2	0 - 255	0 - 100	Crossfade from Static	0% / 0

NOVA II 2x1, NOVA II 1x1

				Color to FX	
18	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Explosion	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Other Effects	0 - 69	0 - 27	Loop	
70 - 255		28 - 100	Stop		
19	Effect Selection	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
150 - 255	61 - 100	Reserved			
20	Effect Parameter 1	0 - 255	0 - 100	See Effect Chart	0% / 0
21	Effect Parameter 2	0 - 255	0 - 100		0% / 0
22	Effect Parameter 3	0 - 255	0 - 100		0% / 0
23	Effect Parameter 4	0 - 255	0 - 100		0% / 0
24	Effect Parameter 5	0 - 255	0 - 100		0% / 0
25	Effect	0 - 255	0 - 100		0% / 0

	<b>Parameter 6</b>				
<b>26</b>	<b>Effect Parameter 7</b>	0 - 255	0 - 100		0% / 0
				*Do not patch "No Effect" range into consoles	

## Profile 118: LE HSIC+ & xy & FX - 16-bit - 2 Pixels (47 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
9 / 10	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
11 / 12	Crossfade	0 - 65535	0 - 100	HSIC+ to xy	0% / 0
13 / 14	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
15 / 16	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>Pixel 2</b>					
17 / 18	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
19 / 20	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
21 / 22	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
23 / 24	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
25 / 26	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
27 / 28	Crossfade	0 - 65535	0 - 100	HSIC+ to xy	0% / 0
29 / 30	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
31 / 32	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>FX</b>					
33	Crossfade 2	0 - 255	0 - 100	Crossfade from Static	0% / 0

NOVA II 2x1, NOVA II 1x1

				Color to FX	
34	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Explosion	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Other Effects	0 - 69	0 - 27	Loop	
70 - 255		28 - 100	Stop		
35	Effect Selection	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
150 - 255	61 - 100	Reserved			
36	Effect Parameter 1	0 - 255	0 - 100	See Effect Chart	0% / 0
37	Effect Parameter 2	0 - 255	0 - 100		0% / 0
38	Effect Parameter 3	0 - 255	0 - 100		0% / 0
39	Effect Parameter 4	0 - 255	0 - 100		0% / 0
40	Effect Parameter 5	0 - 255	0 - 100		0% / 0
41	Effect	0 - 255	0 - 100		0% / 0

	<b>Parameter 6</b>				
<b>42</b>	<b>Effect Parameter 7</b>	0 - 255	0 - 100		0% / 0
<b>43</b>	<b>Effect Parameter 8</b>	0 - 255	0 - 100		0% / 0
<b>44</b>	<b>Effect Parameter 9</b>	0 - 255	0 - 100		0% / 0
<b>45</b>	<b>Effect Parameter 10</b>	0 - 255	0 - 100		0% / 0
<b>46</b>	<b>Effect Parameter 11</b>	0 - 255	0 - 100		0% / 0
<b>47</b>	<b>Effect Parameter 12</b>	0 - 255	0 - 100		0% / 0
				*Do not patch "No Effect" range into consoles	

### Profile 119: LE xy - 8-bit - 2 Pixels (6 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
3	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>Pixel 2</b>					
4	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
5	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
6	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)

### Profile 120: LE xy - 16-bit - 2 Pixels (12 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
5 / 6	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>Pixel 2</b>					
7 / 8	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
9 / 10	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
11 / 12	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)

### Profile 121: LE RGB - 8-bit - 2 Pixels (6 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>CCT is Locked at 6500K</b>					
<b>Pixel 1</b>					
1	Red	0 - 255	0 - 100	Red Intensity	100% / 255
2	Green	0 - 255	0 - 100	Green Intensity	100% / 255
3	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Pixel 2</b>					
4	Red	0 - 255	0 - 100	Red Intensity	100% / 255
5	Green	0 - 255	0 - 100	Green Intensity	100% / 255
6	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255

NOVA II 2x1, NOVA II 1x1

## Profile 122: LE RGB - 16-bit - 2 Pixels (12 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
CCT is Locked at 6500K					
Pixel 1					
1 / 2	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
3 / 4	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
5 / 6	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
Pixel 2					
7 / 8	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
9 / 10	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
11 / 12	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535

## Profile 123: LE iRGB - 8-bit - 2 Pixels (8 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
CCT is Locked at 6500K					
Pixel 1					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	Red	0 - 255	0 - 100	Red Intensity	100% / 255
3	Green	0 - 255	0 - 100	Green Intensity	100% / 255
4	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
Pixel 2					
5	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
6	Red	0 - 255	0 - 100	Red Intensity	100% / 255
7	Green	0 - 255	0 - 100	Green Intensity	100% / 255
8	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255

## Profile 124: LE iRGB - 16-bit - 2 Pixels (16 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>CCT is Locked at 6500K</b>					
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
5 / 6	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
7 / 8	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Pixel 2</b>					
9 / 10	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
11 / 12	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
13 / 14	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
15 / 16	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535

## Profile 125: LE RGBAL - 8-bit - 2 Pixels (10 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Red	0 - 255	0 - 100	Red Intensity	100% / 255
2	Green	0 - 255	0 - 100	Green Intensity	100% / 255
3	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
4	Amber	0 - 255	0 - 100	Amber Intensity	100% / 255
5	Lime	0 - 255	0 - 100	Lime Intensity	100% / 255
<b>Pixel 2</b>					
6	Red	0 - 255	0 - 100	Red Intensity	100% / 255
7	Green	0 - 255	0 - 100	Green Intensity	100% / 255
8	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
9	Amber	0 - 255	0 - 100	Amber Intensity	100% / 255
10	Lime	0 - 255	0 - 100	Lime Intensity	100% / 255

## Profile 126: LE RGBAL - 16-bit - 2 Pixels (20 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
<b>1 / 2</b>	<b>Red</b>	0 - 65535	0 - 100	Red Intensity	100% / 65535
<b>3 / 4</b>	<b>Green</b>	0 - 65535	0 - 100	Green Intensity	100% / 65535
<b>5 / 6</b>	<b>Blue</b>	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>7 / 8</b>	<b>Amber</b>	0 - 65535	0 - 100	Amber Intensity	100% / 65535
<b>9 / 10</b>	<b>Lime</b>	0 - 65535	0 - 100	Lime Intensity	100% / 65535
<b>Pixel 2</b>					
<b>11 / 12</b>	<b>Red</b>	0 - 65535	0 - 100	Red Intensity	100% / 65535
<b>13 / 14</b>	<b>Green</b>	0 - 65535	0 - 100	Green Intensity	100% / 65535
<b>15 / 16</b>	<b>Blue</b>	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>17 / 18</b>	<b>Amber</b>	0 - 65535	0 - 100	Amber Intensity	100% / 65535
<b>19 / 20</b>	<b>Lime</b>	0 - 65535	0 - 100	Lime Intensity	100% / 65535

## Profile 127: LE CCT+ - 8-bit - 2 Pixels (6 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
<b>1</b>	<b>Intensity</b>	0 - 255	0 - 100	0 - 100%	0% / 0
<b>2</b>	<b>CCT</b>	0 - 255	0 - 100	1800K - 20000K	3200K / 20
<b>3</b>	<b>±Green</b>	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
<b>Pixel 2</b>					
<b>4</b>	<b>Intensity</b>	0 - 255	0 - 100	0 - 100%	0% / 0
<b>5</b>	<b>CCT</b>	0 - 255	0 - 100	1800K - 20000K	3200K / 20
<b>6</b>	<b>±Green</b>	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
				*Do not patch "No Effect" range into consoles	

## Profile 128: LE CCT+ - 16-bit - 2 Pixels (12 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
<b>Pixel 2</b>					
7 / 8	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
9 / 10	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
11 / 12	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
				*Do not patch "No Effect" range into consoles	

## Control Channel Profiles - 2 Pixels

### DMX Control Channel Chart

The DMX Control Channel of the Profile should be a 0 value and then moved to the specific DMX Value to execute the command. Once executed, the DMX value should be returned to zero.

DMX			FUNCTION	DESCRIPTION	Time to Save
0	-	10	No function	Nothing	2.5 seconds
11	-	13	Signal Flash Enabled	When sending a Control Channel Command, the Light Flashes to confirm received	2.5 seconds
14	-	16	Signal Flash Disabled	When sending a Control Channel Command, the Light will not flash when a command is received.	2.5 seconds
17	-	19	Sidus BT On		2.5 seconds
20	-	22	Sidus BT Off		2.5 seconds
23	-	25	Sidus BT Reset		2.5 seconds
26	-	28	DMX Smoothing: Off	Snap to Intensities	2.5 seconds / Instant On
29	-	31	DMX Smoothing: Smooth	Smooth to Intensities	2.5 seconds / Instant On
32	-	34	DMX Smoothing: Super Smooth	Super Smooth to Intensities	2.5 seconds / Instant On
35	-	37	DMX Smoothing: Feather	Super Smooth from 0-4%, Snaps from 5 to 100%	2.5 seconds / Instant On
38	-	40	CRMX On	Turns wireless CRMX ON	2.5 seconds
41	-	43	CRMX Off	Turns wireless CRMX OFF	2.5 seconds
44	-	46	CRMX Unlink	TX: Unlink all linked fixtures RX: Unlink the fixture from a CRMX transmitter	2.5 seconds
47	-	49	CRMX Link	If set as a CRMX Transmitter, it will send the Link Signal	2.5 seconds
50	-	52	CRMX Mode RX	If set to a CRMX TX, it will change to RX. If it is off, it will remain off.	2.5 seconds

53	-	55	CRMX Mode TX	If set to a CRMX RX, it will change to TX. If it is off, it will remain off.	2.5 seconds
56	-	58	RDM off	Turns off the RDM	2.5 seconds
59	-	61	RDM on	Turns on the RDM	2.5 seconds
62	-	64	High Speed Mode On	if available	2.5 seconds
65	-	67	High Speed Mode Off	if available	2.5 seconds
68	-	70	Constant Output		2.5 seconds
71	-	73	Maximum Output		2.5 seconds
74	-	76	Studio Mode ON		2.5 seconds
77	-	79	Studio Mode OFF		2.5 seconds
80	-	82	Turn On Fan DMX Control Channel		2.5 seconds
83	-	85	Turn Off Fan DMX Control Channel	Sets Fan to Smart	2.5 seconds
86	-	88	N/A		
89	-	91	N/A		
92	-	94	N/A		
95	-	97	N/A		
98	-	100	Dim curve Linear	Dim curve Linear	2.5 seconds
101	-	103	Dim curve Exponential	Dim curve Exponential	2.5 seconds
104	-	106	Dim curve Logarithmic	Dim curve Logarithmic	2.5 seconds
107	-	109	Dim curve S-Curve	Dim curve S-Curve	2.5 seconds
110	-	172	N/A		2.5 seconds
173	-	175	with Diffuser Calibration	Calibrated with Diffuser	2.5 seconds
176	-	178	No Diffuser Calibration	Calibrated for use without Diffuser accessories	2.5 seconds
179	-	249	Reserved		
250	-	252	Turn On Control Channel	Defaults to On	2.5 seconds
253	-	255	Turn off Control Channel	Commands sent on the DMX Control Channel will be ignored.	2.5 seconds



## Profile 141: LE CCT & RGB & Control - 8-bit - 2 Pixels (17 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
5	Red	0 - 255	0 - 100	Red Intensity	100% / 255
6	Green	0 - 255	0 - 100	Green Intensity	100% / 255
7	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Pixel 2</b>					
8	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
9	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
10	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
11	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
12	Red	0 - 255	0 - 100	Red Intensity	100% / 255
13	Green	0 - 255	0 - 100	Green Intensity	100% / 255
14	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255

NOVA II 2x1, NOVA II 1x1

Control Channels					
15	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
16	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
17	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 142: LE CCT & RGB & Control - 16-bit - 2 Pixels (31 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
9 / 10	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
11 / 12	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
13 / 14	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Pixel 2</b>					
15 / 16	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
17 / 18	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
19 / 20	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
21 / 22	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
23 / 24	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
25 / 26	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
27 / 28	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Control Channels</b>					

NOVA II 2x1, NOVA II 1x1

<b>29</b>	<b>Strobe</b>	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
<b>30</b>	<b>Control Channel</b>	0 - 255	0 - 100	See Control Channel Chart	
<b>31</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 143: LE CCT & RGB & FX & Control - 8-bit - 2 Pixels (27 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
5	Red	0 - 255	0 - 100	Red Intensity	100% / 255
6	Green	0 - 255	0 - 100	Green Intensity	100% / 255
7	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Pixel 2</b>					
8	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
9	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
10	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
11	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
12	Red	0 - 255	0 - 100	Red Intensity	100% / 255
13	Green	0 - 255	0 - 100	Green Intensity	100% / 255
14	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255

NOVA II 2x1, NOVA II 1x1

FX					
15	Crossfade 2	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
16	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	Trigger Explosion	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
		Trigger Other Effects	0 - 69	0 - 27	
70 - 255	28 - 100		Stop		
17	Effect Selection	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
150 - 255	61 - 100	Reserved			
18	Effect Parameter 1	0 - 255	0 - 100	See Effect Chart	0% / 0
19	Effect Parameter 2	0 - 255	0 - 100		0% / 0
20	Effect Parameter 3	0 - 255	0 - 100		0% / 0

21	Effect Parameter 4	0 - 255	0 - 100		0% / 0
22	Effect Parameter 5	0 - 255	0 - 100		0% / 0
23	Effect Parameter 6	0 - 255	0 - 100		0% / 0
24	Effect Parameter 7	0 - 255	0 - 100		0% / 0
<b>Control Channels</b>					
25	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
26	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
27	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 144: LE CCT & RGB & FX & Control - 16-bit - 2 Pixels (46 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
9 / 10	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
11 / 12	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
13 / 14	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 2</b>					
15 / 16	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
17 / 18	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
19 / 20	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
21 / 22	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
23 / 24	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
25 / 26	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535

NOVA II 2x1, NOVA II 1x1

<b>27 / 28</b>	<b>Blue</b>	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>FX</b>					
<b>29</b>	<b>Crossfade 2</b>	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
<b>30</b>	<b>Trigger</b>	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	<b>Trigger Explosion</b>	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
		<b>Trigger Other Effects</b>	0 - 69	0 - 27	
70 - 255	28 - 100		Stop		
<b>31</b>	<b>Effect Selection</b>	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
150 - 255	61 - 100	Reserved			
<b>32</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>33</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>34</b>	<b>Effect Parameter</b>	0 - 255	0 - 100		0% / 0

NOVA II 2x1, NOVA II 1x1

	<b>3</b>				
<b>35</b>	<b>Effect Parameter 4</b>	0 - 255	0 - 100		0% / 0
<b>36</b>	<b>Effect Parameter 5</b>	0 - 255	0 - 100		0% / 0
<b>37</b>	<b>Effect Parameter 6</b>	0 - 255	0 - 100		0% / 0
<b>38</b>	<b>Effect Parameter 7</b>	0 - 255	0 - 100		0% / 0
<b>39</b>	<b>Effect Parameter 8</b>	0 - 255	0 - 100		0% / 0
<b>40</b>	<b>Effect Parameter 9</b>	0 - 255	0 - 100		0% / 0
<b>41</b>	<b>Effect Parameter 10</b>	0 - 255	0 - 100		0% / 0
<b>42</b>	<b>Effect Parameter 11</b>	0 - 255	0 - 100		0% / 0
<b>43</b>	<b>Effect Parameter 12</b>	0 - 255	0 - 100		0% / 0
<b>Control Channels</b>					
<b>44</b>	<b>Strobe</b>	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
<b>45</b>	<b>Control Channel</b>	0 - 255	0 - 100	See Control Channel Chart	
<b>46</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	

NOVA II 2x1, NOVA II 1x1

		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 145: LE CCT & RGB & xy & Control - 8-bit - 2 Pixels (23 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
5	Red	0 - 255	0 - 100	Red Intensity	100% / 255
6	Green	0 - 255	0 - 100	Green Intensity	100% / 255
7	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
8	Crossfade 2	0 - 255	0 - 100	CCTRGB to xy	0% / 0
9	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
10	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>Pixel 2</b>					
11	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
12	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
13	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
14	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0

NOVA II 2x1, NOVA II 1x1

<b>15</b>	<b>Red</b>	0 - 255	0 - 100	Red Intensity	100% / 255
<b>16</b>	<b>Green</b>	0 - 255	0 - 100	Green Intensity	100% / 255
<b>17</b>	<b>Blue</b>	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>18</b>	<b>Crossfade 2</b>	0 - 255	0 - 100	CCTRGB to xy	0% / 0
<b>19</b>	<b>x Coordinate</b>	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
<b>20</b>	<b>y Coordinate</b>	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>Control Channels</b>					
<b>21</b>	<b>Strobe</b>	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
<b>22</b>	<b>Control Channel</b>	0 - 255	0 - 100	See Control Channel Chart	
<b>23</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 146: LE CCT & RGB & xy & Control - 16-bit - 2 Pixels (43 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
9 / 10	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
11 / 12	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
13 / 14	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
15 / 16	Crossfade 2	0 - 65535	0 - 100	CCTRGB to xy	0% / 0
17 / 18	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
19 / 20	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>Pixel 2</b>					
21 / 22	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
23 / 24	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
25 / 26	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
27 / 28	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0

NOVA II 2x1, NOVA II 1x1

<b>29 / 30</b>	<b>Red</b>	0 - 65535	0 - 100	Red Intensity	100% / 65535
<b>31 / 32</b>	<b>Green</b>	0 - 65535	0 - 100	Green Intensity	100% / 65535
<b>33 / 34</b>	<b>Blue</b>	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>35 / 36</b>	<b>Crossfade 2</b>	0 - 65535	0 - 100	CCTRGB to xy	0% / 0
<b>37 / 38</b>	<b>x Coordinate</b>	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
<b>39 / 40</b>	<b>y Coordinate</b>	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>Control Channels</b>					
<b>41</b>	<b>Strobe</b>	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
<b>42</b>	<b>Control Channel</b>	0 - 255	0 - 100	See Control Channel Chart	
<b>43</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 147: LE CCT & RGB & xy & FX & Control - 8-bit - 2 Pixels (33 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0
5	Red	0 - 255	0 - 100	Red Intensity	100% / 255
6	Green	0 - 255	0 - 100	Green Intensity	100% / 255
7	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
8	Crossfade 2	0 - 255	0 - 100	CCTRGB to xy	0% / 0
9	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
10	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>Pixel 2</b>					
11	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
12	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
13	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
14	Crossfade	0 - 255	0 - 100	White Light to RGB	0% / 0

NOVA II 2x1, NOVA II 1x1

<b>15</b>	<b>Red</b>	0 - 255	0 - 100	Red Intensity	100% / 255
<b>16</b>	<b>Green</b>	0 - 255	0 - 100	Green Intensity	100% / 255
<b>17</b>	<b>Blue</b>	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>18</b>	<b>Crossfade 2</b>	0 - 255	0 - 100	CCTRGB to xy	0% / 0
<b>19</b>	<b>x Coordinate</b>	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
<b>20</b>	<b>y Coordinate</b>	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>FX</b>					
<b>21</b>	<b>Crossfade 3</b>	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
<b>22</b>	<b>Trigger</b>	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	<b>Trigger Explosion</b>	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	<b>Trigger Other Effects</b>	0 - 69	0 - 27	Loop	
70 - 255		28 - 100	Stop		
<b>23</b>	<b>Effect Selection</b>	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
150 - 255	61 - 100	Reserved			
<b>24</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0

25	Effect Parameter 2	0 - 255	0 - 100		0% / 0
26	Effect Parameter 3	0 - 255	0 - 100		0% / 0
27	Effect Parameter 4	0 - 255	0 - 100		0% / 0
28	Effect Parameter 5	0 - 255	0 - 100		0% / 0
29	Effect Parameter 6	0 - 255	0 - 100		0% / 0
30	Effect Parameter 7	0 - 255	0 - 100		0% / 0
<b>Control Channels</b>					
31	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
32	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
33	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 148: LE CCT & RGB & xy & FX & Control - 16-bit - 2 Pixels (58 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0
9 / 10	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
11 / 12	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
13 / 14	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
15 / 16	Crossfade 2	0 - 65535	0 - 100	CCTRGB to xy	0% / 0
17 / 18	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
19 / 20	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>Pixel 2</b>					
21 / 22	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
23 / 24	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
25 / 26	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
27 / 28	Crossfade	0 - 65535	0 - 100	White Light to RGB	0% / 0

NOVA II 2x1, NOVA II 1x1

<b>29 / 30</b>	<b>Red</b>	0 - 65535	0 - 100	Red Intensity	100% / 65535
<b>31 / 32</b>	<b>Green</b>	0 - 65535	0 - 100	Green Intensity	100% / 65535
<b>33 / 34</b>	<b>Blue</b>	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>35 / 36</b>	<b>Crossfade 2</b>	0 - 65535	0 - 100	CCTRGB to xy	0% / 0
<b>37 / 38</b>	<b>x Coordinate</b>	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
<b>39 / 40</b>	<b>y Coordinate</b>	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>FX</b>					
<b>41</b>	<b>Crossfade 3</b>	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
<b>42</b>	<b>Trigger</b>	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	<b>Trigger Explosion</b>	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
		<b>Trigger Other Effects</b>	0 - 69	0 - 27	
70 - 255	28 - 100		Stop		
<b>43</b>	<b>Effect Selection</b>	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
150 - 255	61 - 100	Reserved			
<b>44</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0

45	Effect Parameter 2	0 - 255	0 - 100		0% / 0
46	Effect Parameter 3	0 - 255	0 - 100		0% / 0
47	Effect Parameter 4	0 - 255	0 - 100		0% / 0
48	Effect Parameter 5	0 - 255	0 - 100		0% / 0
49	Effect Parameter 6	0 - 255	0 - 100		0% / 0
50	Effect Parameter 7	0 - 255	0 - 100		0% / 0
51	Effect Parameter 8	0 - 255	0 - 100		0% / 0
52	Effect Parameter 9	0 - 255	0 - 100		0% / 0
53	Effect Parameter 10	0 - 255	0 - 100		0% / 0
54	Effect Parameter 11	0 - 255	0 - 100		0% / 0
55	Effect Parameter 12	0 - 255	0 - 100		0% / 0
<b>Control Channels</b>					
56	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
57	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
58	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	

		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 149: LE HSI+ & Control - 8-bit - 2 Pixels (9 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>CCT is Locked at 6500K</b>					
<b>Pixel 1</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
3	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
<b>Pixel 2</b>					
4	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
5	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
6	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
<b>Control Channels</b>					
7	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
8	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
9	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 150: LE HSI - 16-bit - 2 Pixels (15 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>CCT is Locked at 6500K</b>					
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
5 / 6	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
<b>Pixel 2</b>					
7 / 8	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
9 / 10	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
11 / 12	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
<b>Control Channels</b>					
13	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
14	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
15	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 151: LE HSIC+ & Control - 8-bit - 2 Pixels (13 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
5	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
<b>Pixel 2</b>					
6	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
7	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
8	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
9	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
10	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
<b>Control Channels</b>					
11	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	

		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
<b>12</b>	<b>Control Channel</b>	0 - 255	0 - 100	See Control Channel Chart	
<b>13</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 152: LE HSIC+ & Control - 16-bit - 2 Pixels (23 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
9 / 10	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
<b>Pixel 2</b>					
11 / 12	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
13 / 14	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
15 / 16	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
17 / 18	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
19 / 20	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
<b>Control Channels</b>					
21	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	

		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
<b>22</b>	<b>Control Channel</b>	0 - 255	0 - 100	See Control Channel Chart	
<b>23</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 153: LE HSIC+ & FX & Control - 8-bit - 2 Pixels (23 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	<b>Intensity</b>	0 - 255	0 - 100	0 - 100%	0% / 0
2	<b>CCT</b>	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	<b>±Green</b>	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	<b>Hue</b>	0 - 255	0 - 100	0 to 359.9°	0% / 0
5	<b>Saturation</b>	0 - 255	0 - 100	White Light to RGB	0% / 0
<b>Pixel 2</b>					
6	<b>Intensity</b>	0 - 255	0 - 100	0 - 100%	0% / 0
7	<b>CCT</b>	0 - 255	0 - 100	1800K - 20000K	3200K / 20
8	<b>±Green</b>	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
9	<b>Hue</b>	0 - 255	0 - 100	0 to 359.9°	0% / 0
10	<b>Saturation</b>	0 - 255	0 - 100	White Light to RGB	0% / 0
<b>FX</b>					
11	<b>Crossfade</b>	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
12	<b>Trigger</b>	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	

NOVA II 2x1, NOVA II 1x1

		70 - 255	28 - 100	Stop	
	<b>Trigger Explosion</b>	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	<b>Trigger Other Effects</b>	0 - 69	0 - 27	Loop	
		70 - 255	28 - 100	Stop	
<b>13</b>	<b>Effect Selection</b>	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
150 - 255	61 - 100	Reserved			
<b>14</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>15</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>16</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0
<b>17</b>	<b>Effect Parameter 4</b>	0 - 255	0 - 100		0% / 0
<b>18</b>	<b>Effect Parameter 5</b>	0 - 255	0 - 100		0% / 0

19	Effect Parameter 6	0 - 255	0 - 100		0% / 0
20	Effect Parameter 7	0 - 255	0 - 100		0% / 0
<b>Control Channels</b>					
21	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
22	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
23	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
			# High Mode applies to the NOVA II 1x1 only		

## Profile 154: LE HSIC+ & FX & Control - 16-bit - 2 Pixels (38 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
9 / 10	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
<b>Pixel 2</b>					
11 / 12	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
13 / 14	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
15 / 16	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
17 / 18	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
19 / 20	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
<b>FX</b>					
21	Crossfade	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
22	Trigger	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	

NOVA II 2x1, NOVA II 1x1

		70 - 255	28 - 100	Stop	
	<b>Trigger Explosion</b>	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	<b>Trigger Other Effects</b>	0 - 69	0 - 27	Loop	
		70 - 255	28 - 100	Stop	
<b>23</b>	<b>Effect Selection</b>	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
	150 - 255	61 - 100	Reserved		
<b>24</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>25</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>26</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0
<b>27</b>	<b>Effect Parameter 4</b>	0 - 255	0 - 100		0% / 0
<b>28</b>	<b>Effect Parameter 5</b>	0 - 255	0 - 100		0% / 0

29	Effect Parameter 6	0 - 255	0 - 100		0% / 0
30	Effect Parameter 7	0 - 255	0 - 100		0% / 0
31	Effect Parameter 8	0 - 255	0 - 100		0% / 0
32	Effect Parameter 9	0 - 255	0 - 100		0% / 0
33	Effect Parameter 10	0 - 255	0 - 100		0% / 0
34	Effect Parameter 11	0 - 255	0 - 100		0% / 0
35	Effect Parameter 12	0 - 255	0 - 100		0% / 0
<b>Control Channels</b>					
36	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
37	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
38	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the	

				NOVA II 1x1 only
--	--	--	--	------------------

## Profile 155: LE HSIC+ & xy & Control - 8-bit - 2 Pixels (19 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
5	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
6	Crossfade	0 - 255	0 - 100	HSIC+ to xy	0% / 0
7	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
8	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>Pixel 2</b>					
9	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
10	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
11	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
12	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
13	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
14	Crossfade	0 - 255	0 - 100	HSIC+ to xy	0% / 0

NOVA II 2x1, NOVA II 1x1

<b>15</b>	<b>x Coordinate</b>	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
<b>16</b>	<b>y Coordinate</b>	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>Control Channels</b>					
<b>17</b>	<b>Strobe</b>	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
<b>18</b>	<b>Control Channel</b>	0 - 255	0 - 100	See Control Channel Chart	
<b>19</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 156: LE HSIC+ & xy & Control - 16-bit - 2 Pixels (35 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
9 / 10	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
11 / 12	Crossfade	0 - 65535	0 - 100	HSIC+ to xy	0% / 0
13 / 14	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
15 / 16	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>Pixel 2</b>					
17 / 18	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
19 / 20	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
21 / 22	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
23 / 24	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
25 / 26	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
27 / 28	Crossfade	0 - 65535	0 - 100	HSIC+ to xy	0% / 0

NOVA II 2x1, NOVA II 1x1

<b>29 / 30</b>	<b>x Coordinate</b>	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
<b>31 / 32</b>	<b>y Coordinate</b>	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>Control Channels</b>					
<b>33</b>	<b>Strobe</b>	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
<b>34</b>	<b>Control Channel</b>	0 - 255	0 - 100	See Control Channel Chart	
<b>35</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 157: LE HSIC+ & xy & FX & Control - 8-bit - 2 Pixels (29 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
4	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
5	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0
6	Crossfade	0 - 255	0 - 100	HSIC+ to xy	0% / 0
7	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
8	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>Pixel 2</b>					
9	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
10	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
11	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
12	Hue	0 - 255	0 - 100	0 to 359.9°	0% / 0
13	Saturation	0 - 255	0 - 100	White Light to RGB	0% / 0

<b>14</b>	<b>Crossfade</b>	0 - 255	0 - 100	HSIC+ to xy	0% / 0
<b>15</b>	<b>x Coordinate</b>	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
<b>16</b>	<b>y Coordinate</b>	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>FX</b>					
<b>17</b>	<b>Crossfade 2</b>	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
<b>18</b>	<b>Trigger</b>	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	<b>Trigger Explosion</b>	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	<b>Trigger Other Effects</b>	0 - 69	0 - 27	Loop	
70 - 255		28 - 100	Stop		
<b>19</b>	<b>Effect Selection</b>	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
	150 - 255	61 - 100	Reserved		
<b>20</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>21</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>22</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0

NOVA II 2x1, NOVA II 1x1

23	Effect Parameter 4	0 - 255	0 - 100		0% / 0
24	Effect Parameter 5	0 - 255	0 - 100		0% / 0
25	Effect Parameter 6	0 - 255	0 - 100		0% / 0
26	Effect Parameter 7	0 - 255	0 - 100		0% / 0
<b>Control Channels</b>					
27	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
28	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
29	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 158: LE HSIC+ & xy & FX & Control - 16-bit - 2 Pixels (50 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
7 / 8	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
9 / 10	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0
11 / 12	Crossfade	0 - 65535	0 - 100	HSIC+ to xy	0% / 0
13 / 14	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
15 / 16	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>Pixel 2</b>					
17 / 18	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
19 / 20	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
21 / 22	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
23 / 24	Hue	0 - 65535	0 - 100	0 to 359.9°	0% / 0
25 / 26	Saturation	0 - 65535	0 - 100	White Light to RGB	0% / 0

<b>27 / 28</b>	<b>Crossfade</b>	<b>0 - 65535</b>	<b>0 - 100</b>	<b>HSIC+ to xy</b>	<b>0% / 0</b>
<b>29 / 30</b>	<b>x Coordinate</b>	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
<b>31 / 32</b>	<b>y Coordinate</b>	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>FX</b>					
<b>33</b>	<b>Crossfade 2</b>	0 - 255	0 - 100	Crossfade from Static Color to FX	0% / 0
<b>34</b>	<b>Trigger</b>	0 - 9	0 - 4	Loop	0% / 0
		10 - 69	5 - 27	Trigger	
		70 - 255	28 - 100	Stop	
	<b>Trigger Explosion</b>	0 - 69	0 - 27	Trigger	
		70 - 255	28 - 100	Stop	
		<b>Trigger Other Effects</b>	0 - 69	0 - 27	
70 - 255	28 - 100		Stop		
<b>35</b>	<b>Effect Selection</b>	0 - 9	0 - 4	Club Lights	0% / 0
		10 - 19	5 - 8	Paparazzi	
		20 - 29	9 - 12	Lightning	
		30 - 39	13 - 16	TV	
		40 - 49	17 - 20	Candle	
		50 - 59	21 - 24	Fire	
		60 - 69	25 - 28	Strobe	
		70 - 79	29 - 32	Explosion	
		80 - 89	33 - 36	Faulty Bulb	
		90 - 99	37 - 40	Pulsing	
		100 - 109	41 - 44	Welding	
		110 - 119	45 - 48	Cop Car	
		120 - 129	49 - 52	Color Chase	
		130 - 139	53 - 56	Party Lights	
		140 - 149	57 - 60	Fireworks	
150 - 255	61 - 100	Reserved			
<b>36</b>	<b>Effect Parameter 1</b>	0 - 255	0 - 100	See Effect Chart	0% / 0
<b>37</b>	<b>Effect Parameter 2</b>	0 - 255	0 - 100		0% / 0
<b>38</b>	<b>Effect Parameter 3</b>	0 - 255	0 - 100		0% / 0

NOVA II 2x1, NOVA II 1x1

39	Effect Parameter 4	0 - 255	0 - 100		0% / 0
40	Effect Parameter 5	0 - 255	0 - 100		0% / 0
41	Effect Parameter 6	0 - 255	0 - 100		0% / 0
42	Effect Parameter 7	0 - 255	0 - 100		0% / 0
43	Effect Parameter 8	0 - 255	0 - 100		0% / 0
44	Effect Parameter 9	0 - 255	0 - 100		0% / 0
45	Effect Parameter 10	0 - 255	0 - 100		0% / 0
46	Effect Parameter 11	0 - 255	0 - 100		0% / 0
47	Effect Parameter 12	0 - 255	0 - 100		0% / 0
<b>Control Channels</b>					
48	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
49	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
50	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the	

NOVA II 2x1, NOVA II 1x1

				NOVA II 1x1 only
--	--	--	--	------------------

## Profile 159: LE xy & Control - 8-bit - 2 Pixels (9 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
3	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>Pixel 2</b>					
4	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
5	x Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.4234 / 136)
6	y Coordinate	0 - 255	0 - 100	0 - 0.8	3200K (.3989 / 125)
<b>Control Channels</b>					
7	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
8	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
9	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 160: LE xy & Control - 16-bit - 2 Pixels (15 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
5 / 6	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>Pixel 2</b>					
7 / 8	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
9 / 10	x Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.4234 / 34684)
11 / 12	y Coordinate	0 - 65535	0 - 100	0 - 0.8	3200K (.3989 / 32686)
<b>Control Channels</b>					
13	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
14	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
15	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 161: LE RGB & Control - 8-bit - 2 Pixels (9 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>CCT is Locked at 6500K</b>					
<b>Pixel 1</b>					
1	Red	0 - 255	0 - 100	Red Intensity	100% / 255
2	Green	0 - 255	0 - 100	Green Intensity	100% / 255
3	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Pixel 2</b>					
4	Red	0 - 255	0 - 100	Red Intensity	100% / 255
5	Green	0 - 255	0 - 100	Green Intensity	100% / 255
6	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Control Channels</b>					
7	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
8	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
9	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 162: LE RGB & Control - 16-bit - 2 Pixels (15 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>CCT is Locked at 6500K</b>					
<b>Pixel 1</b>					
<b>1 / 2</b>	<b>Red</b>	0 - 65535	0 - 100	Red Intensity	100% / 65535
<b>3 / 4</b>	<b>Green</b>	0 - 65535	0 - 100	Green Intensity	100% / 65535
<b>5 / 6</b>	<b>Blue</b>	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Pixel 2</b>					
<b>7 / 8</b>	<b>Red</b>	0 - 65535	0 - 100	Red Intensity	100% / 65535
<b>9 / 10</b>	<b>Green</b>	0 - 65535	0 - 100	Green Intensity	100% / 65535
<b>11 / 12</b>	<b>Blue</b>	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Control Channels</b>					
<b>13</b>	<b>Strobe</b>	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
<b>14</b>	<b>Control Channel</b>	<b>0 - 255</b>	<b>0 - 100</b>	<b>See Control Channel Chart</b>	
<b>15</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 163: LE iRGB & Control - 8-bit - 2 Pixels (11 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>CCT is Locked at 6500K</b>					
<b>Pixel 1</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	Red	0 - 255	0 - 100	Red Intensity	100% / 255
3	Green	0 - 255	0 - 100	Green Intensity	100% / 255
4	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Pixel 2</b>					
5	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
6	Red	0 - 255	0 - 100	Red Intensity	100% / 255
7	Green	0 - 255	0 - 100	Green Intensity	100% / 255
8	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Control Channels</b>					
9	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
10	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
11	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 164: LE iRGB & Control - 16-bit - 2 Pixels (19 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>CCT is Locked at 6500K</b>					
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
5 / 6	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
7 / 8	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Pixel 2</b>					
9 / 10	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
11 / 12	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
13 / 14	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
15 / 16	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Control Channels</b>					
17	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
18	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
19	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 165: LE RGBAL & Control - 8-bit - 2 Pixels (13 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Red	0 - 255	0 - 100	Red Intensity	100% / 255
2	Green	0 - 255	0 - 100	Green Intensity	100% / 255
3	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
4	Amber	0 - 255	0 - 100	Amber Intensity	100% / 255
5	Lime	0 - 255	0 - 100	Lime Intensity	100% / 255
<b>Pixel 2</b>					
6	Red	0 - 255	0 - 100	Red Intensity	100% / 255
7	Green	0 - 255	0 - 100	Green Intensity	100% / 255
8	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
9	Amber	0 - 255	0 - 100	Amber Intensity	100% / 255
10	Lime	0 - 255	0 - 100	Lime Intensity	100% / 255
<b>Control Channels</b>					
11	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
12	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
13	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the	

NOVA II 2x1, NOVA II 1x1

				NOVA II 1x1 only
--	--	--	--	------------------

## Profile 166: LE RGBAL & Control - 16-bit - 2 Pixels (23 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
3 / 4	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
5 / 6	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
7 / 8	Amber	0 - 65535	0 - 100	Amber Intensity	100% / 65535
9 / 10	Lime	0 - 65535	0 - 100	Lime Intensity	100% / 65535
<b>Pixel 2</b>					
11 / 12	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
13 / 14	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
15 / 16	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
17 / 18	Amber	0 - 65535	0 - 100	Amber Intensity	100% / 65535
19 / 20	Lime	0 - 65535	0 - 100	Lime Intensity	100% / 65535
<b>Control Channels</b>					
21	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
22	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
23	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	



## Profile 167: LE CCT+ & Control - 8-bit - 2 Pixels (9 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
2	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
3	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
<b>Pixel 2</b>					
4	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
5	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
6	±Green	0 - 255	0 - 100	-G to 0G to +G	Neutral / 50% / 137
		0 - 10	0 - 4	No Effect*	
		11 - 20	5 - 8	-100 / Full Minus Green	
		21 - 119	9 - 46	-99% - -1%	
		120 - 145	47 - 57	0% / Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	100% / Full Plus Green	
<b>Control Channels</b>					
7	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
8	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
9	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	

		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 168: LE CCT+ & Control - 16-bit - 2 Pixels (15 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
3 / 4	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
5 / 6	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
<b>Pixel 2</b>					
7 / 8	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
9 / 10	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
11 / 12	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
<b>Control Channels</b>					
13	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
14	Control Channel	0 - 255	0 - 100	See Control Channel Chart	

<b>15</b>	<b>Fan Mode</b>	0 - 38		0 - 15	Smart	0% / 0
		39 - 77		16 - 30	High	
			39 - 50	16 - 19	Max#	
			51 - 77	20 - 30	High#	
		78 - 115		31 - 45	Medium	
		116 - 153		46 - 60	Low	
		154 - 191		61 - 75	Delayed	
		192 - 255		76 - 100	Silent	
				*Do not patch "No Effect" range into consoles		
				# High Mode applies to the NOVA II 1x1 only		

## Color Space Profiles - 2 Pixels

### Profile 181: VRGB & Control - 8-bit - 2 Pixels (12 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Red	0 - 255	0 - 100	Red Intensity	100% / 255
2	Green	0 - 255	0 - 100	Green Intensity	100% / 255
3	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Pixel 2</b>					
4	Red	0 - 255	0 - 100	Red Intensity	100% / 255
5	Green	0 - 255	0 - 100	Green Intensity	100% / 255
6	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Global Parameters</b>					
7	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
8	±Green	0 - 10	0 - 4	Neutral / No Effect*	Neutral / 50% / 137
		11 - 20	5 - 8	Full Minus Green	
		21 - 119	9 - 47	-99% - -1%	
		120 - 145	48 - 57	Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	Full Plus Green	
9	Color Space	0 - 255	0 - 100	SEE COLOR SPACE CHART	
<b>Control Channels</b>					
10	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
11	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
12	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	

NOVA II 2x1, NOVA II 1x1

			39 - 50	16 - 19	Max#	
			51 - 77	20 - 30	High#	
			78 - 115	31 - 45	Medium	
			116 - 153	46 - 60	Low	
			154 - 191	61 - 75	Delayed	
			192 - 255	76 - 100	Silent	
					*Do not patch "No Effect" range into consoles	
					# High Mode applies to the NOVA II 1x1 only	

## Profile 182: VRGB & Control - 16-bit - 2 Pixels (20 ch.)

Channel	Function	Value	Percent	Description	Default
<b>Pixel 1</b>					
1 / 2	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
3 / 4	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
5 / 6	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Pixel 2</b>					
7 / 8	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
9 / 10	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
11 / 12	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Global Parameters</b>					
13 / 14	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
15 / 16	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
17	Color Space	0 - 255	0 - 100	SEE COLOR SPACE CHART	
<b>Control Channels</b>					
18	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	

NOVA II 2x1, NOVA II 1x1

19	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
20	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 183: VRGB-I & Control - 8-bit - 2 Pixels (13 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Red	0 - 255	0 - 100	Red Intensity	100% / 255
2	Green	0 - 255	0 - 100	Green Intensity	100% / 255
3	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Pixel 2</b>					
4	Red	0 - 255	0 - 100	Red Intensity	100% / 255
5	Green	0 - 255	0 - 100	Green Intensity	100% / 255
6	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Global Parameters</b>					
7	Intensity	0 - 255	0 - 100	0 - 100%	0% / 0
8	CCT	0 - 255	0 - 100	1800K - 20000K	3200K / 20
9	±Green	0 - 10	0 - 4	Neutral / No Effect*	Neutral / 50% / 137
		11 - 20	5 - 8	Full Minus Green	
		21 - 119	9 - 47	-99% - -1%	
		120 - 145	48 - 57	Neutral	
		146 - 244	58 - 96	1% - 99%	
		245 - 255	97 - 100	Full Plus Green	
10	Color Space	0 - 255	0-100	SEE COLOR SPACE CHART	
<b>Control Channels</b>					
11	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
12	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
13	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	

NOVA II 2x1, NOVA II 1x1

		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 184: VRGB & Control - 16-bit - 2 Pixels (22 ch.)

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
3 / 4	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
5 / 6	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Pixel 2</b>					
7 / 8	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
9 / 10	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
11 / 12	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Global Parameters</b>					
13 / 14	Intensity	0 - 65535	0 - 100	0 - 100%	0% / 0
15 / 16	CCT	0 - 65535	0 - 100	1800K - 20000K	3200K / 5041
17 / 18	±Green	0 - 65535	0 - 100	-G to 0G to +G	Neutral / 50% / 35390
		0 - 2621	0 - 4	No Effect*	
		2622 - 5243	5 - 8	-100 / Full Minus Green	
		5244 - 30146	9 - 47	-99% - -1%	
		30147 - 37355	48 - 57	0% / Neutral	
		37356 - 62914	58 - 96	1% - 99%	
		62915 - 65535	97 - 100	100% / Full Plus Green	
19	Color Space	0 - 255	0-100	SEE COLOR SPACE CHART	
<b>Control Channels</b>					
20	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
21	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
22	Fan Mode	0 - 38	0 - 15	Smart	0% / 0

NOVA II 2x1, NOVA II 1x1

		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				*Do not patch "No Effect" range into consoles	
				# High Mode applies to the NOVA II 1x1 only	

### Profile 185: VRGB-CS & Control - 8-bit - 2 Pixels (10 ch.)

CCT Locked at 6500K					
Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Red	0 - 255	0 - 100	Red Intensity	100% / 255
2	Green	0 - 255	0 - 100	Green Intensity	100% / 255
3	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Pixel 2</b>					
4	Red	0 - 255	0 - 100	Red Intensity	100% / 255
5	Green	0 - 255	0 - 100	Green Intensity	100% / 255
6	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Global Parameters</b>					
7	Color Space	0 - 255	0 - 100	SEE COLOR SPACE CHART	
<b>Control Channels</b>					
8	Strobe	0 - 13	0 - 5	Off	0% / 0

NOVA II 2x1, NOVA II 1x1

		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
<b>9</b>	<b>Control Channel</b>	0 - 255	0 - 100	See Control Channel Chart	
<b>10</b>	<b>Fan Mode</b>	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 186: VRGB-CS & Control - 16-bit - 2 Pixels (16 ch.)

CCT Locked at 6500K

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
3 / 4	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
5 / 6	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Pixel 1</b>					
7 / 8	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
9 / 10	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
11 / 12	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Global Parameters</b>					
13	Color Space	0 - 255	0-100	SEE COLOR SPACE CHART	
<b>Control Channels</b>					
14	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
15	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
16	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

NOVA II 2x1, NOVA II 1x1



## Profile 187: VRGB-709 & Control - 8-bit - 2 Pixels (9 ch.)

CCT Locked at 6500K @ SRGB					
Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Red	0 - 255	0 - 100	Red Intensity	100% / 255
2	Green	0 - 255	0 - 100	Green Intensity	100% / 255
3	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Pixel 2</b>					
4	Red	0 - 255	0 - 100	Red Intensity	100% / 255
5	Green	0 - 255	0 - 100	Green Intensity	100% / 255
6	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Global Parameters</b>					
<b>Control Channels</b>					
7	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
8	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
9	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	



## Profile 188: VRGB-709 - 16-bit - 2 Pixels (15 ch.)

CCT Locked at 6500K @ SRGB

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1 / 2	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
3 / 4	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
5 / 6	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Pixel 2</b>					
7 / 8	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
9 / 10	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
11 / 12	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Global Parameters</b>					
<b>Control Channels</b>					
13	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
14	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
15	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 189: VRGB-sRGB - 8-bit - 2 Pixels (9 ch.)

CCT Locked at 6500K @ SRGB

Channel	Function	Value	Percent	Description	Default % / DMX
<b>Pixel 1</b>					
1	Red	0 - 255	0 - 100	Red Intensity	100% / 255
2	Green	0 - 255	0 - 100	Green Intensity	100% / 255
3	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Pixel 2</b>					
4	Red	0 - 255	0 - 100	Red Intensity	100% / 255
5	Green	0 - 255	0 - 100	Green Intensity	100% / 255
6	Blue	0 - 255	0 - 100	Blue Intensity	100% / 255
<b>Global Parameters</b>					
<b>Control Channels</b>					
7	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
8	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
9	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	
		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

## Profile 190: VRGB-sRGB - 16-bit - 2 Pixels (15 ch.)

CCT Locked at 6500K @ SRGB

Channel	Function	Value	Percent	Description	Default
<b>Pixel 1</b>					
1 / 2	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
3 / 4	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
5 / 6	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Pixel 2</b>					
7 / 8	Red	0 - 65535	0 - 100	Red Intensity	100% / 65535
9 / 10	Green	0 - 65535	0 - 100	Green Intensity	100% / 65535
11 / 12	Blue	0 - 65535	0 - 100	Blue Intensity	100% / 65535
<b>Global Parameters</b>					
<b>Control Channels</b>					
13	Strobe	0 - 13	0 - 5	Off	0% / 0
		14 - 128	6 - 50	Random ( 0.4Hz -> 25Hz )	
		129 - 255	51 - 100	Constant ( 0.4Hz -> 25Hz )	
14	Control Channel	0 - 255	0 - 100	See Control Channel Chart	
15	Fan Mode	0 - 38	0 - 15	Smart	0% / 0
		39 - 77	16 - 30	High	
		39 - 50	16 - 19	Max#	
		51 - 77	20 - 30	High#	
		78 - 115	31 - 45	Medium	
		116 - 153	46 - 60	Low	
		154 - 191	61 - 75	Delayed	

		192 - 255	76 - 100	Silent	
				# High Mode applies to the NOVA II 1x1 only	

# Color Space Chart

## VRGB

Value	Percent	Description	EOTF	RGB->XYZ Matrix
Default % / DMX 100% / 255				
0 - 255	0 - 100			
0 - 10	0 - 4	<b>Broadcast SDR</b>	<b>Gamma 2.4</b>	<b>Rec709</b>
11 - 20	5 - 8	<b>sRGB</b>	<b>sRGB</b>	<b>Rec709</b>
21 - 30	9 - 12	Broadcast Rec709 HDR (relative)	ST2084 (PQ) (Relative)	Rec709
31 - 40	13 - 16	Broadcast Rec709 HDR (1000 nits Scaled)	ST2084 1000 nits Scaled (relative)	Rec709
41 - 50	17 - 20	Broadcast HDR: HLG (Relative)	HLG 1200 nits Scaled (Relative)	Rec709
51 - 60	21 - 24	<b>Display P3</b>	<b>sRGB</b>	<b>P3 D65</b>
61 - 70	25 - 28	P3 HDR (relative)	ST2084 (PQ) (Relative)	P3 D65
71 - 80	29 - 32	<b>P3 HDR (1000 nits Scaled)</b>	<b>ST2084 1000 nits Scaled (relative)</b>	<b>P3 D65</b>
81 - 90	33 - 35	<b>P3 HDR: HLG (Relative)</b>	<b>HLG 1200 nits Scaled (Relative)</b>	<b>P3 D65</b>
91 - 100	36 - 39	Rec2020 SDR	Gamma 2.4	Rec2020
101 - 110	40 - 43	Rec2100 HDR (Relative)	ST2084 (PQ) (Relative)	Rec2020
111 - 120	44 - 47	<b>Rec2100 HDR (1000 nits Scaled)</b>	<b>ST2084 1000 nits Scaled (relative)</b>	Rec2020
121 - 130	48 - 51	<b>Rec2100 HDR: HLG (Relative)</b>	<b>HLG 1200 nits Scaled (Relative)</b>	Rec2020
131 - 140	52 - 55	Apple Log	Apple Log	Rec2020
141 - 150	56 - 59	ACES AP1 (relative)	ACEScct (relative)	ACES AP1
151 - 160	60 - 63	<b>ACES AP0</b>	<b>Linear</b>	<b>ACES AP0</b>
161 - 244	64 - 96	RESERVED	RESERVED	RESERVED

NOVA II 2x1, NOVA II 1x1

245 - 255	97 - 100	<b>Aputure Color Space</b>	<b>Linear</b>	<b>Aputure Gamut</b>
-----------	----------	----------------------------	---------------	----------------------